




INTERNATIONAL APPLICATION PUBLISHED UNDER THE PATENT COOPERATION TREATY (PCT)

(51) International Patent Classification ⁶ : H01J 37/32		A1	(11) International Publication Number: WO 97/08734
			(43) International Publication Date: 6 March 1997 (06.03.97)
(21) International Application Number: PCT/US96/14157		(81) Designated States: JP, KP, European patent (AT, BE, CH, DE, DK, ES, FI, FR, GB, GR, IE, IT, LU, MC, NL, PT, SE).	
(22) International Filing Date: 28 August 1996 (28.08.96)			
(30) Priority Data: 08/521,669 30 August 1995 (30.08.95) US 08/597,577 2 February 1996 (02.02.96) US		Published <i>With international search report. Before the expiration of the time limit for amending the claims and to be republished in the event of the receipt of amendments.</i>	
(71) Applicant: APPLIED MATERIALS, INC. [US/US]; Patent Counsel, P.O. Box 450A, Santa Clara, CA 95052 (US).			
(72) Inventors: COLLINS, Kenneth; 165 Knightshaven Way, San Jose, CA 95111 (US). RICE, Michael; 785 Claret Court, Pleasanton, CA 94566 (US). TROW, John; 162 Knightshaven Way, San Jose, CA 95111 (US). BUCHBERGER, Douglas; 421 Czerny Street, Tracy, CA 95376 (US). ASKARIAN, Eric; 1332 Pauline Drive, Sunnyvale, CA 94087 (US). TSUI, Joshua; 613 Azevedo Court, Santa Clara, CA 95051 (US). GROECHEL, David; 27985 Via Ventana, Los Altos Hills, CA 94022 (US). HUNG, Raymond; 1282 Burkette Drive, San Jose, CA 95129 (US).			
(74) Agent: SGARBOSSA, Pete; Applied Materials, Inc., P.O. Box 450A, Santa Clara, CA 95052 (US).			

(54) Title: PLASMA REACTOR HAVING AN INDUCTIVE ANTENNA COUPLING POWER THROUGH A PARALLEL PLATE ELECTRODE

(57) Abstract

The invention is embodied by a plasma reactor for processing a workpiece, including a reactor enclosure (105) defining a processing chamber (100), a semiconductor window (110), a base (120) within the chamber (100) for supporting the workpiece (125) during processing thereof, a gas inlet system (137) for admitting a plasma precursor gas into the chamber (100), and an inductive antenna (145) adjacent a side of the semiconductor window (110) opposite the base (120) for coupling power into the interior of the chamber (100) through the semiconductor window electrode (110).



FOR THE PURPOSES OF INFORMATION ONLY

Codes used to identify States party to the PCT on the front pages of pamphlets publishing international applications under the PCT.

AM	Armenia	GB	United Kingdom	MW	Malawi
AT	Austria	GE	Georgia	MX	Mexico
AU	Australia	GN	Guinea	NE	Niger
BB	Barbados	GR	Greece	NL	Netherlands
BE	Belgium	HU	Hungary	NO	Norway
BF	Burkina Faso	IE	Ireland	NZ	New Zealand
BG	Bulgaria	IT	Italy	PL	Poland
BJ	Benin	JP	Japan	PT	Portugal
BR	Brazil	KE	Kenya	RO	Romania
BY	Belarus	KG	Kyrgystan	RU	Russian Federation
CA	Canada	KP	Democratic People's Republic of Korea	SD	Sudan
CF	Central African Republic	KR	Republic of Korea	SE	Sweden
CG	Congo	KZ	Kazakhstan	SG	Singapore
CH	Switzerland	LI	Liechtenstein	SI	Slovenia
CI	Côte d'Ivoire	LK	Sri Lanka	SK	Slovakia
CM	Cameroon	LR	Liberia	SN	Senegal
CN	China	LT	Lithuania	SZ	Swaziland
CS	Czechoslovakia	LU	Luxembourg	TD	Chad
CZ	Czech Republic	LV	Latvia	TG	Togo
DE	Germany	MC	Monaco	TJ	Tajikistan
DK	Denmark	MD	Republic of Moldova	TT	Trinidad and Tobago
EE	Estonia	MG	Madagascar	UA	Ukraine
ES	Spain	ML	Mali	UG	Uganda
FI	Finland	MN	Mongolia	US	United States of America
FR	France	MR	Mauritania	UZ	Uzbekistan
GA	Gabon			VN	Viet Nam

**PLASMA REACTOR HAVING AN
INDUCTIVE ANTENNA COUPLING POWER
THROUGH A PARALLEL PLATE ELECTRODE**

5

BACKGROUND OF THE INVENTION

Technical Field:

The invention relates to a plasma reactor having parallel plates for interposition therebetween of a workpiece to be processed, such as a semiconductor wafer, and an inductive coil antenna coupling RF power through one of the parallel plates into the interior of the reactor.

Background Art:

Inductively coupled plasma reactors for processing microelectronic semiconductor wafers, such as the type of reactor disclosed in U.S. Patent No. 4,948,458 to Ogle, enjoy important advantages over parallel-plate capacitively coupled plasma reactors. For example, inductively coupled plasma reactors achieve higher plasma ion densities (e.g., on the order of 10^{11} ions/cm³). Moreover, plasma ion density and plasma ion energy can be independently controlled in an inductively coupled plasma reactor by applying bias power to the workpiece or wafer. In contrast, capacitively coupled reactors typically provide relatively lower plasma ion densities (e.g., on the order of only 10^{10} ions/cm³) and generally cannot provide independent control of ion density and ion energy. The superior ion-to-neutral density ratio provided by an inductively coupled plasma etch reactor used to etch silicon dioxide, for example, provides superior performance at small etch geometries (e.g., below 0.5 micron feature size) including better etch anisotropy, etch profile and etch selectivity. In contrast, parallel plate capacitively coupled plasma reactors typically stop etching at feature sizes on the order of about 0.25 microns, or at least exhibit inferior etch selectivity and etch profile due to an inferior ion-to-neutral density ratio.

The inductively coupled plasma reactor disclosed in U.S. Patent No. 4,948,458 referred to above has a planar coil overlying the chamber ceiling and facing the semiconductor wafer being processed, thereby providing an optimally uniform RF induction field over the surface of the wafer. For this purpose, the ceiling, which seals the reactor chamber so that it can be evacuated, must be fairly transmissive to the RF induction field from the coil and is therefore a dielectric, such as quartz. It should be noted here that such a ceiling could be made from dielectric materials other than quartz, such as aluminum oxide. However other materials such as aluminum oxide tend produce greater contamination than quartz due to sputtering.

An advantage of capacitively coupled plasma reactors is that the chamber volume can be greatly reduced by reducing the space between the parallel plate electrodes, thereby better confining or concentrating the plasma over the workpiece, while the reactor can be operated at relatively high chamber pressure (e.g., 200 mTorr). In contrast, inductively coupled plasma reactors require a larger volume due to the large skin depth of the RF induction field, and must be operated at a lower chamber pressure (e.g., 10 mTorr) to avoid loss of plasma ions due to recombination and higher pumping speed. In commercial embodiments of the inductively coupled reactor of U.S. Patent No. 4,948,458 referred to above, the requirement of a large chamber volume is met by a fairly large area side wall. The lack of any other RF ground return (due to the requirement of a dielectric window to admit the RF induction field from the overhead coil) means that the chamber side wall should be conductive and act as the principal ground or RF return plane. However, the side wall is a poor ground plane, as it has many discontinuities, such as a slit valve for wafer ingress and egress, gas distribution ports or apparatus and so forth. Such discontinuities give rise to non-uniform

current distribution, which distort plasma ion distribution relative to the wafer surface. The resulting sideways current flow toward the side wall contributes to non-uniform plasma ion distribution relative to the wafer surface.

5 One approach for combining capacitive and inductive coupling is to provide a side coil wound around the side wall of a parallel plate plasma reactor, as disclosed in European Patent Document Publication No. 0 520 519 A1 by Collins et al. For this purpose, the cylindrical chamber
10 side wall must be a nonconductor such as quartz in order to admit the RF induction field of the side coil into the chamber. The main problem with this type of plasma reactor is that it is liable to exhibit processing non-uniformity across the wafer surface. For example, the etch rate is
15 much greater at the wafer periphery and much slower at the wafer center, thereby constricting the process window. In fact, the etch process may actually stop near the wafer center while continuing at the wafer periphery. The disposition of the induction coil antenna along the side
20 wall of the reactor chamber, the relatively short (e.g., 2 cm) skin depth (or depth within which most of the RF power is absorbed) toward the chamber center, and the introduction of the etch precursor gas into the reactor chamber from the side, confine most of the etchant ion and radical production
25 to the vicinity of the chamber side wall or around the wafer periphery. The phrase "etchant ion and radical" as employed in this specification refers to the various chemical species that perform the etch reaction, including fluoro-carbon ions and radicals as well as fluoro-hydrocarbon ions and
30 radicals. The population of free fluorine ions and radicals is preferably minimized by well-known techniques if a selective etch process is desired. Energetic electrons generated by the plasma source power interact with the process precursor gas and thereby produce the required
35 etchant ions and radicals and, furthermore, produce

molecular or atomic carbon necessary for polymerization employed in sophisticated etch processes. The etch process near the wafer center is dependent upon such energetic electrons traveling from the vicinity of the chamber side wall and reaching the wafer center before recombining along the way by collisions with neutral species or ions, so that the etch process is not uniform across the wafer surface. These problems are better understood in light of the role polymerization plays in the etch process.

Polymerization employing fluoro-carbon (C_xF_x) or fluoro-hydrocarbon chemistry is employed in a typical silicon dioxide etch process, for example, to enhance etch anisotropy or profile and etch selectivity, as described in Bariya et al., "A Surface Kinetic Model for Plasma Polymerization with Application to Plasma Etching," Journal of the Electrochemical Society, Volume 137, No. 8 (August 1990), pp. 2575-2581 at page 1. An etch precursor gas such as a fluoro-carbon like C_2F_6 or a fluoro-hydrocarbon introduced into the reactor chamber dissociates by inelastic collisions with energetic electrons in the plasma into etchant ions and radicals as well as carbon. As noted above, such etchant ions and radicals include fluoro-carbon or fluoro-hydrocarbon ions and radicals, for example, and free fluorine ions and radicals. The free fluorine ions and radicals are preferably minimized through scavenging, for example, if the etch process is to be selective with respect to a certain material such as polysilicon. The carbon and at least some of the fluoro-carbon or fluoro-hydrocarbon ions and radicals are polymer-forming. Also present in the plasma are excited neutrals or undissociated species and etch by-products. The polymer-forming radicals and carbon enhance etch profile as follows: By forming only on the side-walls of etch features (formation on the horizontal surfaces being prevented by the energetic downward ion flux from the plasma), polymers can block lateral etching and

thereby produce anisotropic (narrow and deep) profiles. The polymer-forming ions and radicals also enhance silicon oxide etch selectivity because polymer generally does not form on the silicon oxide under favorable conditions but does form on silicon or other materials which are not to be etched but which may underlie a silicon oxide layer being etched. Thus, as soon as an overlying silicon oxide layer has completely etched through to expose an underlying polysilicon layer, the polymer-forming ions and radicals in the plasma that contact the exposed polysilicon layer immediately begin to form a polymer layer, inhibiting further etching.

Such polymerization during the etch process requires a careful balance of etchant and polymer, the etchant concentration typically being at a depletion level to avoid inhibition of appropriate polymer formation. As a result, a significant proportion of etchant ions and radicals formed near the wafer periphery are consumed before reaching the wafer center, further depleting the etch ion concentration over the wafer center. This leads to a lower etch rate or etch stopping near the wafer center.

One reason that there are more ions at the wafer periphery is that the location of the inductive coil at the side wall causes hotter ion-producing electrons to be generated in the vicinity of the side wall, such electrons cooling off and/or being consumed by recombination before reaching the center so that less production of etchant ions and radicals occurs over the wafer center. Moreover, introduction of the etchant precursor gas from the side and coupling of plasma source power from the side produces a non-uniform etchant ion/radical distribution favoring the side. Many of the ions and radicals formed near side (over the wafer periphery) are consumed by etching the quartz side wall and are not available to etch the wafer center, while etchant ion/radical-forming energetic electrons generated

near the side are lost to collisions with other species before reaching the wafer center, thus reducing the etchant ion concentration at the wafer center. (It should be noted that the etching of the quartz side wall greatly increases the cost of operating the reactor because it consumes a very expensive item --the quartz side wall, which must be periodically replaced.) The relative lack of etchant ions near the wafer center permits faster formation of polymer at the wafer center, so much so that in some cases the polymer formation overwhelms the etch process and stops it, particularly at feature sizes less than 0.5 microns. Such etch stopping may occur either at larger etch features, at shallower etch depths or at shorter etch times.

The converse of the foregoing is that the relative plentitude of etchant ions and radicals near the wafer periphery can, under selected processing conditions, so impede polymerization as to impair etch selectivity, possibly leading to punchthrough of the underlying layer near the wafer periphery, in addition to causing a much higher etch rate at the wafer periphery. A related problem is that the hotter electrons near the chamber side wall/wafer periphery providing more energetic plasma ions in that vicinity, coupled with the oxygen released by the etching of the quartz side wall mentioned above, erodes the edges of the photoresist mask near the wafer periphery. Such erosion leads to faceting, in which the corners defined by the photoresist mask are etched, giving rise to an undesirable tapered etch profile.

From the foregoing, it is clear that there is a trade-off between avoiding punchthrough and faceting at the wafer edge and avoiding etch stopping at the wafer center, dictating a very narrow window of processing parameters within which a successful etch process may be realized across the entire wafer surface. To avoid the overetching the wafer periphery, the concentration of etchant ions and

radicals in the plasma relative to other particles (e.g., polymer-forming ions or radicals and carbon) may be decreased, which risks etch-stopping at the wafer center. Conversely, to avoid etch-stopping at the wafer center, the concentration of etchant ions in the plasma may be increased, which risks punchthrough or faceting near the wafer periphery. Thus, the process window for successfully etching the entire wafer is very narrow.

In the parallel plate plasma reactor, the concentration of free fluorine in the plasma can be controlled by introducing a scavenging article, such as silicon, near or at the top of the reactor chamber. Silicon atoms physically etched (sputtered), chemically etched or reactive ion etched from the scavenging article combine with the fluorine ions and radicals, thereby reducing fluorine ion and radical concentration in the plasma. By controlling the rate at which silicon atoms are physically or chemically etched from the scavenging article, the amount of free fluorine ions and radicals in the plasma may be regulated (e.g., reduced) as desired to meet the narrow processing window mentioned above. The physical or chemical etch rates can be controlled by controlling the temperature of the scavenging article and/or by controlling the rate of ion-bombardment on the scavenging article. The surface of the scavenging article may be activated (to release silicon atoms into the plasma) either by RF power or by heating. By holding the scavenging article's temperature below the temperature at which polymerization occurs, the polymers accumulate on the scavenging article surface and block any release therefrom of silicon atoms. By raising the scavenging article's temperature above the condensation temperature, the surface is free from polymers, thus permitting the release of silicon atoms into the plasma. Further increasing the temperature increases the rate at which silicon atoms are released from the scavenging surface into the plasma. As

for activating the scavenging article by RF power, the rate of ion bombardment of the scavenging article is affected by the RF potential or bias applied to the top parallel plate electrode adjacent the scavenging article. Reducing the free fluorine concentration in this manner has the effect of not only decreasing etch rate but also enriching the carbon content of the polymer, thus increasing the effect of the polymer on the etch process to guard against punch through at the wafer periphery, but increasing the risk of etch stopping at the wafer center. Conversely, increasing the free fluorine concentration not only increases the etch rate but also depletes the carbon content of the polymer, thus decreasing the effect of polymerization on the etch process, thus decreasing the risk of etch stopping at the wafer center but weakening the protection against punch through at the wafer periphery.

The narrow processing window is also met by regulating the polymer-forming ion and radical concentration in the plasma. This is accomplished by regulating the rate at which such polymer-forming radicals and ions are lost from the plasma by polymerization onto the chamber ceiling or sidewalls (or a scavenging article) or the rate at which polymer deposits are sputtered from the ceiling or sidewalls (or scavenging article). The polymerization rate at the ceiling is affected by regulating the ceiling temperature above or below the polymerization temperature. The rate at which such polymer deposits on the ceiling are etched and released into the plasma is affected by the following factors: the RF power applied to the ceiling electrode, temperature, chamber pressure, gas flow rate, inductive source power and other parameters.

Thus, in order to meet the narrow processing window, in general the relative concentrations of free fluorine and polymer-forming ions and radicals in the plasma may be controlled by regulating the temperature of the chamber

ceiling or side walls or a scavenging article (if any) and/or by regulating the RF power applied to the to overhead/ceiling parallel plate electrode.

Thus, it is seen that the parallel-plate plasma reactor with the induction coil wound around its cylindrical side wall has the advantage of providing its ceiling electrode as a uniform ground plane over the entire wafer surface, but confines plasma ion production to the vicinity of the chamber side wall, so that plasma processing is weaker at the wafer center and stronger at the wafer periphery. The overhead planar coil plasma reactor has the advantage of a more uniform RF induction field relative to the wafer surface, so that ion production is not confined to the wafer periphery, but suffers from the lack of any uniform ground plane over the wafer, so that plasma ion current flow to the side walls distorts the plasma.

It is an object of the invention to combine the advantages of an inductively coupled plasma reactor having an overhead planar induction coil antenna with the advantages of a parallel plate electrode capacitively coupled plasma reactor in a single reactor without suffering the disadvantages or problems described above. Specifically, it is an object of the invention to provide an inductively coupled parallel plate electrode plasma reactor which exhibits uniform plasma processing across the entire wafer surface, so as to widen the plasma processing window, thus permitting a wider range in processing parameters, such as chamber pressure for example.

It is an object of the invention to provide an induction coil antenna whose physical disposition and/or power distribution pattern is relatively uniform with reference to the entire wafer surface so that plasma ion production is not predominantly at the vicinity of the chamber side wall, while at the same time providing a uniform ground plane in close proximity to the entire wafer

surface so as to avoid plasma current flow to the chamber side wall. It is a further object of the invention to employ such a ground plane in a manner that effectively confines the plasma closer to the top surface of the wafer so as to minimize interaction with the chamber side wall.

It is another object of the invention to eliminate or reduce consumable materials such as quartz or ceramics in the chamber walls, so as to avoid depletion of plasma ions near the chamber walls and consumption of expensive reactor components through etching of such materials.

It is a further object of the invention to enhance processing uniformity at the wafer center relative to the wafer periphery in such a reactor by providing a uniform etch and polymer precursor gas distribution. Specifically, it is an object of the invention to introduce such gas from an optimum radial location of the chamber, such as from the chamber center and/or from the chamber periphery, whichever optimizes process uniformity across the wafer surface. For example, where etch rate is low at the wafer center and high at the wafer periphery, the gas is preferably introduced from the center of the ceiling rather than from near the periphery of the ceiling.

It is an additional object of the invention to enhance processing uniformity at the wafer center relative to the wafer periphery in such a reactor by enhancing (or reducing, if desired) the RF induction field over the wafer center relative to the RF induction field over the wafer periphery. Specifically, it is an additional object of the invention to provide separate or independent control of the strength of the RF induction field over the wafer center and independent control of the strength of the RF induction field over the wafer periphery, so that the radial distribution of the RF induction field across the wafer surface is adjustable to optimize plasma processing uniformity across the wafer surface.

In a typical plasma processing chamber used for selective etching of thin films on a semiconductor wafer, a combination of etch and deposition processes are employed simultaneously. Polymer forms on surfaces that are either sufficiently cold (below the temperature threshold of polymerization) or on which ion bombardment is below a threshold energy (the threshold ion energy sufficient to offset the polymer deposition rate on that surface). The temperature threshold and the threshold ion energy depend upon the material of the surface. Deposition can occur on the wafer as well as the process chamber surfaces. Control of the deposition on the wafer as well as the process chamber surfaces is critical to controlling the selective etch process. Polymer deposition on interior surfaces of reactor chamber walls is required in cases where the material of the chamber walls is incompatible with the process being carried out on the wafer. One example of this is where the chamber walls are aluminum and the process being carried out is plasma etching of silicon dioxide. Deposition of polymer on the chamber wall surfaces prevents introduction of aluminum into the process by preventing plasma ion sputtering of the chamber walls.

Conventional techniques for controlling polymer deposition required the user to choose between the following two options:

(1) Keeping the process chamber surfaces below the threshold temperature or keeping the ion energy below the threshold ion energy in order to cause polymer deposition on the surfaces;

(2) Keeping process chamber surfaces above the threshold temperature or keeping the ion energy above the threshold ion energy in order to prevent polymer deposition on the surfaces.

The problem with option (1) is that the polymer accumulated on the surface must be removed periodically,

either by manual (wet) cleaning, by plasma (dry) cleaning, or by replacing the contaminated parts. Otherwise, flaking of the polymer will occur, leading to contamination of the chamber. Cleaning the reactor chamber requires the reactor
5 operation be interrupted during the entire cleaning process, which represents a significant loss of productivity and increases the cost of operating the reactor. Problems associated with the plasma cleaning process include not only loss of productivity but also loss of consumable materials
10 in the chamber and contamination.

The problem with option (2) is that etching of chamber surfaces occurs because the surfaces are exposed. Typically, these surfaces are either aluminum or quartz. For aluminum surfaces, etching creates contaminant by-
15 products that can destroy the integrity of the plasma processing of the wafer, as mentioned hereinabove. For quartz surfaces, the etching can occur at such a high rate that the quartz parts must be replaced periodically at a significant cost in parts and lost production time.
20 Moreover, some transition to colder surfaces --in other regions of the chamber such as the pumping annulus-- must be provided.

It is therefore an additional object of the invention to eliminate the requirement to periodically clean the
25 reactor chamber interior. It is a further object of the invention to prevent the collection of polymer on chamber surfaces in the processing region of the chamber. It is a related object to control the etch rate of those same chamber surfaces. It is a further object of the invention
30 to provide appropriate transition from the processing region of the chamber by confining the plasma to the processing region. It is a yet further object of the invention to collect any residual polymer-forming species in areas outside the processing region of the chamber such as the
35 pumping annulus.

DISCLOSURE OF THE INVENTION

The invention is embodied in a plasma reactor for processing a workpiece, including a reactor enclosure defining a processing chamber, a semiconductor window, a base within the chamber for supporting the workpiece during processing thereof, a gas inlet system for admitting a plasma precursor gas into the chamber, and an inductive antenna adjacent a side of the semiconductor window opposite the base for coupling power into the interior of the chamber through the semiconductor window. The workpiece may be a planar substrate, the semiconductor window (and the inductive antenna) may be either inside the chamber or outside of the chamber. In the latter case the semiconductor window may be a ceiling portion of the reactor enclosure generally parallel to and overlying the planar substrate, and the inductive antenna may overlie the ceiling portion to face the planar substrate through the semiconductor window. Alternatively, the semiconductor window may be a sidewall portion of the reactor enclosure generally perpendicular to and surrounding a periphery of the substrate, the inductive antenna being adjacent the sidewall portion. Preferably, the inductive antenna overlying the ceiling portion includes an arcuately extending elongate conductor disposed generally parallel to the plane of the planar substrate and may be either planar or dome-shaped. The inductive antenna adjacent the sidewall portion may be a conductive coil wound around the sidewall portion.

In one embodiment, the semiconductor window, in addition to shielding the inductive antenna, may also be an electrode, in which case an electrical terminal is connected thereto. In this case the semiconductor window is referred to as a semiconductor window electrode.

In one embodiment, a bias RF power source is coupled to the substrate, and the electrical terminal of the

semiconductor window electrode is connected so as to enable the semiconductor window electrode to be a counter electrode to the bias RF power source coupled to the substrate, by being grounded, for example, thereby providing a uniform
5 ground plane over the workpiece.

Another embodiment includes a power splitter having one output coupled to the semiconductor window electrode and another output coupled to the substrate and an input for receiving power from a common source. Yet another
10 embodiment includes a first power source coupled to the semiconductor window electrode and a second power source coupled to the planar substrate.

The inductive antenna may include an inner antenna portion overlying a center of the planar substrate and an
15 outer antenna portion overlying a periphery of the planar substrate and electrically separated from the inner antenna portion. This embodiment may include a power splitter having one output coupled to the semiconductor window electrode and another output coupled to the inductive
20 antenna and an input for receiving power from a common source. Alternatively, an RF power splitter may split RF power between the inner and outer inductive antenna portions.

In accordance with one feature of the invention, a
25 power splitter has one output coupled to the planar substrate and another output coupled to the inductive antenna and an input for receiving power from a common source. In this case, the electrical terminal of the semiconductor window electrode may be connected to RF
30 ground. Alternatively, an independent RF power generator may be coupled to the electrical terminal of the semiconductor window.

The ceiling semiconductor window electrode with the overhead inductive antenna and the sidewall semiconductor
35 window electrode with the side inductive antenna element may

be combined in a single reactor. In this case, a power splitter may be employed having one output coupled to the inductive antenna overlying the ceiling portion and another output coupled to the inductive antenna element adjacent the sidewall portion, and an input for receiving power from a common source.

The semiconductor window and the workpiece may be separately driven with RF power, while the workpiece may be a counter electrode for the semiconductor window electrode, and the semiconductor window electrode may be a counter electrode for the workpiece. This may be accomplished by employing a first RF power source of a first frequency coupled to the semiconductor window electrode, a second RF power source of a second frequency coupled to the workpiece, a first ground pass filter connected between RF ground and the semiconductor window electrode, the first ground pass filter blocking RF power around the first frequency and passing RF power around the second frequency, and a second ground pass filter coupled between RF ground and the workpiece, the second ground pass filter blocking RF power around the second frequency and passing RF power around the first frequency. Furthermore, a first isolation filter may be connected between the first RF power source and the semiconductor window electrode for blocking RF power near the second frequency, and a second isolation filter may be connected between the second RF power source and the workpiece for block RF power near the first frequency.

In accordance with another feature, a conductive backplane lies on an external surface of the semiconductor window electrode, the conductive backplane being connected directly to the electrical terminal, the conductive electrode including plural apertures therein for admitting an induction field of the inductive antenna through the conductive backplane. Preferably, the conductive backplane includes plural conductive radial arms separated by the

apertures, and the apertures have a characteristic width on the order of approximately a thickness of the semiconductor window electrode.

5 In accordance with a further feature, a structurally supportive substrate may be bonded to an exterior surface of the semiconductor window electrode. The conductive backplane may be inserted between the window electrode and the supportive substrate if desired, the conductive backplane being connected directly to the electrical
10 terminal. The structurally supportive substrate may be an antenna holder supporting the inductive antenna. The antenna holder may be an insulator or a conductor (insulated from the inductive antenna, however). The conductive antenna holder may serve as a conductive backplane on an
15 exterior surface of the semiconductor window electrode. In one embodiment, the inductive antenna includes an elongate conductor extended in an arcuate path, and the conductive antenna holder includes a elongate groove extending in the arcuate path and holding the elongate conductor, the groove being open at a surface of the conductive antenna holder
20 facing the semiconductor window electrode. In another embodiment, the conductive antenna holder includes an recess in a surface of the conductive antenna holder facing the semiconductor window electrode, and the inductive antenna includes plural elongate conductive turns held within the
25 recess.

In accordance with one implementation, the inductive antenna is a non-concentrically arcuately extending elongate conductor. In one case, the non-concentrically arcuately
30 extending elongate conductor includes a center conductive element and plural spirals radiating outwardly from the center conductive element. In another case, the non-concentrically arcuately extending elongate conductor includes a circumferential conductive element and plural

spirals radiating inwardly from the circumferential conductive element.

5 In accordance with another implementation, the inductive antenna has a non-planar path such as a three-dimensional helix or dual concentric three-dimensional helical paths or stacked spiral paths.

10 The gas inlet system preferably includes a set of gas inlet ports through the semiconductor window electrode over the planar substrate. These gas inlet ports may be concentrated over the wafer center and/or may be distributed to overlie the wafer periphery. A center gas feed top may be sealed onto an exterior surface of the semiconductor window electrode, forming a gas manifold between the center gas feed top and the semiconductor window electrode, the gas manifold encompassing the gas inlet ports. In one embodiment, a semiconductor baffle extends across the manifold and dividing the manifold into a pair of sub-manifolds, one of the sub-manifolds being adjacent the center gas feed top and the other of the sub-manifolds being adjacent the gas inlet ports, and plural gas feed passages through the semiconductor baffle offset from the gas inlet ports.

20 In order to eliminate the need to passivate interior chamber surfaces by polymer deposition, an all-semiconductor processing region is provided in the chamber. This is accomplished in one embodiment by providing a semiconductor skirt extending down from the semiconductor window or ceiling, thereby providing an all-semiconductor enclosure confining the plasma within a processing region overlying the wafer. The semiconductor material surrounding the processing region is compatible with plasma processes such as silicon dioxide etching and therefore may be exposed to the plasma in the chamber without risk of process contamination. In one embodiment, the semiconductor enclosure is temperature-controlled to prevent polymer

25

30

35

deposition. In another embodiment, polymer deposition on the semiconductor enclosure is prevented by applying an appropriate electrical bias to the semiconductor enclosure to facilitate sufficient ion bombardment or sputtering to prevent polymer accumulation on the semiconductor enclosure. In yet another embodiment, polymer accumulation on the semiconductor enclosure is prevented by a combination of temperature control and sputtering promoted by electrical bias. The sputtering reduces the temperature at which the semiconductor enclosure must be maintained to prevent polymer accumulation. Each of these embodiments provides a revolutionary advance in the art because the need to periodically clean the reactor chamber interior surfaces has been virtually eliminated, thereby greatly increasing the productivity of the reactor.

In order to prevent the plasma from escaping the processing region, plasma confinement magnets are provided around the opening between the processing region and the pumping annulus. In another embodiment, plasma confinement magnets are provided around the wafer slit valve to confine the plasma within the processing region.

Alternatively, or in addition to the plasma confinement magnets, plasma leakage may be prevented by providing passages (for permitting wafer ingress and egress, for example) which are narrow or have a high aspect ratio. Alternatively, or in addition, such passages may be meandering and formed by overlapping baffles.

In order to handle polymer precursor material that escapes from the processing region of the chamber (e.g., into the pumping annulus of the chamber), surfaces outside the processing region (e.g., within the pumping annulus) are maintained well below the polymer condensation temperature to cause condensation and deposition of stray polymer precursor materials thereon. Such surfaces may be in the

form of a removable cold liner. The region containing such surfaces (e.g., the pumping annulus) is isolated from the plasma processing region over the wafer so that there is no electrical biasing, plasma heating, large temperature variations or ion bombardment on such surfaces as would cause flaking of the deposited polymer precursor materials therefrom. Otherwise, such flaking would re-introduce the polymer materials back into the plasma and could contaminate the wafer.

In order to compensate for processing non-uniformities (e.g., etch rate non-uniformity) between the wafer edge and the wafer center, the semiconductor window may be divided into electrically separate inner and outer (side and center, or side wall and ceiling) elements to which plasma source RF power may be applied in different proportions, for the most uniform processing across the wafer. RF power may be split between the elements or applied separately. In addition, an overhead RF induction coil may also be divided into electrically separate coils to which plasma source power may be applied in different proportions. In addition to an overhead RF induction coil, a side induction coil may be wound around the skirt portion of the semiconductor enclosure and powered independently of the overhead coil, the semiconductor enclosure acting as a window for inductive coupling from both the overhead coil and the side coil as well as an electrode to which RF power may be applied.

Processing uniformity is enhanced in another aspect of the all-semiconductor processing region by providing independent edge and center gas feeds through which the plasma precursor gases may be fed at different rates and/or with different gas mixtures, these differences being selected to provide the greatest wafer center-to-edge processing uniformity. The edge gas feed affects plasma composition over the wafer edge while the center gas feed affects plasma composition over the wafer center. The edge

gas feed includes gas inlets from the side wall facing toward the wafer center or gas inlets from the ceiling facing downwardly toward the wafer edge or gas inlets near the wafer pedestal facing upwardly toward the wafer edge.

5 The center gas feed may be a single gas inlet over the wafer center or multiple gas inlets distributed over the wafer center or a showerhead.

In accordance with another aspect of the invention, no electrical bias is applied to the semiconductor enclosure, so that it is not required that it be made of semiconductor materials in this case. For example, the enclosure may be formed of such dielectrics as silicon nitride. In any case, it must be formed of a good thermal conductor material so that the temperature may be precisely controlled relative to the polymer condensation temperature.

10

15

A collar provided around the circumference of the wafer pedestal is also temperature-controlled to prevent accumulation of polymer thereon. The collar may be formed of a semiconductor material. Alternatively, the collar may be a dielectric such as silicon nitride or quartz.

20

BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1 illustrates a first embodiment of the plasma reactor invention having a planar coil antenna overlying a planar silicon ceiling.

25

FIG. 2 is a graph illustrating the normalized forward voltage transmission coefficient from a transmitting RF coil to a receiving RF coil with a planar silicon window of FIG. 1 in between the transmitting and receiving RF coils.

FIG. 3 is a graph illustrating the normalized forward voltage transmission coefficient from a transmitting RF coil to a receiving RF coil with a cylindrical version of the silicon window in between the transmitting and receiving RF coils.

30

FIG. 4 illustrates an embodiment of the invention employing power splitting between the silicon ceiling and the wafer pedestal.

5 FIG. 5 illustrates an embodiment of the invention employing separate RF power sources to drive the wafer pedestal, the overhead induction coil and the silicon ceiling.

10 FIG. 6 illustrates an embodiment of the invention in which the overhead inductive antenna is divided into separately powered concentric inner and outer windings.

FIG. 7 illustrates an embodiment employing a side inductive antenna wound around a cylindrical silicon side wall.

15 FIG. 8 illustrates an embodiment corresponding to that of FIG. 7 in which power from a single RF power source is split between the silicon side wall and the wafer pedestal.

FIG. 9 illustrates an embodiment employing separate RF generators driving the silicon side wall, the wafer pedestal and the inductive side antenna.

20 FIG. 10 illustrates an embodiment combining the silicon ceiling and overhead inductive antenna with the silicon side wall and the inductive side coil wound thereabout.

25 FIG. 11 illustrates an embodiment corresponding to that of FIG. 10 employing power splitting between the silicon side wall and the wafer pedestal.

30 FIG. 12 illustrates an embodiment in which the silicon ceiling, the silicon side wall, the overhead inductive antenna and the side inductive antenna are separately driven with RF power.

FIG. 13A illustrates an embodiment corresponding to that of FIG. 1 employing a dome-shaped silicon ceiling.

FIG. 13B illustrates an embodiment corresponding to that of FIG. 4 employing a dome-shaped silicon ceiling.

FIG. 13C illustrates an embodiment corresponding to that of FIG. 5 employing a dome-shaped silicon ceiling.

FIG. 13D illustrates an embodiment corresponding to that of FIG. 6 employing a dome-shaped silicon ceiling.

5 FIG. 14 illustrates an embodiment having a dome-shaped silicon ceiling and an overlying inductive antenna having a dome-shaped portion overlying the ceiling and continuing into a cylindrical portion wrapped around the cylindrical side wall.

10 FIG. 15 illustrates an embodiment corresponding to that of FIG. 14 but in which the dome-shaped and cylindrical portions of the inductive antenna are isolated from one another and separately driven with RF power.

15 FIG. 16 illustrates an embodiment corresponding to that of FIG. 6 in which power from a common RF generator is split between the inner and outer inductive antennas.

20 FIG. 17A illustrates an embodiment corresponding to that of FIG. 15 in which power from a common RF generator is split between the dome-shaped and cylindrical inductive antenna portions.

FIG. 17B illustrates an embodiment having separate inner and outer dome-shaped inductive antennas between which power from a common RF generator is split.

25 FIG. 18 illustrates an embodiment corresponding to that of FIG. 10 in which power from a common RF generator is split between the overhead inductive antenna and the side inductive antenna.

30 FIG. 19 illustrates an embodiment corresponding to that of FIG. 1 in which power from a common RF generator is split between the overhead inductive antenna and the silicon ceiling.

35 FIG. 20 illustrates an embodiment corresponding to that of FIG. 1 in which power from a common RF generator is split between the overhead inductive antenna and the wafer pedestal.

FIG. 21 illustrates an embodiment corresponding to that of FIG. 13A having a dome-shaped ceiling in which power from a common RF generator is split between the overhead inductive antenna and the dome-shaped silicon ceiling.

5 FIG. 22 illustrates an embodiment corresponding to that of FIG. 13A having a dome-shaped ceiling in which power from a common RF generator is split between the overhead inductive antenna and the wafer pedestal.

10 FIG. 23 illustrates an embodiment in which the wafer pedestal and the silicon ceiling are separately driven with RF power and each serves as the counter electrode for the other.

15 FIG. 24 illustrates an embodiment corresponding to that of FIG. 23 in which the silicon ceiling is dome-shaped.

FIG. 25A is a side view of an embodiment of the silicon ceiling including a conductive back plane.

FIG. 25B is a top view of one embodiment of the conductive back plane.

20 FIG. 25C is a top view of another embodiment of the conductive back plane.

FIG. 26 is a side view of an embodiment of the silicon ceiling which is bonded to a supportive substrate.

25 FIG. 27 is a side view of an embodiment corresponding to that of FIG. 26 in which the supportive substrate is an insulative holder of the overhead inductive antenna.

FIG. 28 is a side view of an embodiment of the invention in which the antenna holder is conductive.

30 FIG. 29 is a side view of an embodiment corresponding to that of FIG. 28 in which the conductive antenna holder has a pair of annular apertures containing the inner and outer overhead inductive antennas.

FIG. 30A is a top view of a non-concentric embodiment of the overhead inductive antenna.

FIGS. 30B and 30C are side views of alternative implementations of the inductive antenna of FIG. 30A having planar and dome-shaped shapes, respectively.

5 FIG. 31A is a top view of another non-concentric embodiment of the overhead inductive antenna.

FIGS. 31B and 31C are side views of alternative implementations of the inductive antenna of FIG. 31A having planar and dome shapes, respectively.

10 FIG. 32 is a cross-sectional side view of a dual cylindrical helix embodiment of the overhead inductive antenna.

FIG. 33 is a cross-sectional side view of a pair of concentric cylindrical helix inductive antennas of the type illustrated in FIG. 32 for the inner and outer antennas of
15 FIG. 16.

FIG. 34 is a cross-sectional side view of an embodiment of the overhead inductive antenna consisting a layers of inductive antennas.

20 FIGS. 35A through 35E illustrate one embodiment of a center gas feed silicon ceiling, of which FIG. 35A is a bottom perspective view of the gas feed top, FIG. 35B is a bottom perspective view of an annular seal therefor, FIG. 35C is a cross-sectional view of the seal of FIG. 35B, FIG. 35D is a top perspective view of the silicon ceiling showing the gas feed holes and FIG. 35E is a partial cross-sectional
25 view of the silicon ceiling of FIG. 35D.

FIG. 36A is a cross-sectional view of another embodiment of the center gas feed silicon ceiling having a pair of gas plenums separated by a silicon wafer baffle.

30 FIG. 36B illustrates an alternative embodiment corresponding to FIG. 36A.

FIG. 37A illustrates how a Faraday shield may be included in the embodiment of FIG. 1.

35 FIG. 37B is a top view of the Faraday shield of FIG. 37A.

FIG. 38A illustrates how a Faraday shield may be included in the embodiment of FIG. 10 having a dome-shaped ceiling.

FIG. 38B illustrates how a Faraday shield may be included in the embodiments of FIGS. 7-9 having a cylindrical semiconductor window electrode and inductive antenna.

FIG. 39A is a detailed cross-sectional side view of a preferred implementation of the invention.

FIG 39B is an axial cross-sectional view of the conductor employed in the overhead inductive antenna.

FIG. 40 illustrates an alternative embodiment in which the semiconductor window and inductive antenna are inside the reactor chamber.

FIG. 41A illustrates an embodiment corresponding to FIG. 40 in which the semiconductor window is dome-shaped.

FIG. 41B illustrates an embodiment corresponding to FIG. 40 in which the semiconductor window is cylindrical and the inductive coil is cylindrical.

FIGS. 42 and 43 illustrate, respectively, side and top views of a segmented version of the semiconductor window electrode.

FIG. 44 illustrates an embodiment corresponding to that of FIG. 42 in which the semiconductor window is dome-shaped.

FIG. 45 illustrates an embodiment in which RF power is split between the semiconductor window electrode and a sidewall electrode, which itself may be a segmented portion of the semiconductor window electrode.

FIGS. 46 and 47 illustrate modifications of the embodiments of FIGS. 42 and 44 in which the outer segment of the semiconductor window electrode is grounded and RF power

is split between the center segment of the semiconductor window electrode and the wafer pedestal.

FIG. 48A is a cut-away side view of a plasma reactor of one embodiment of the invention having an all-semiconductor enclosure confining plasma within a processing region over the wafer.

FIG. 48B is a cut-away side view of a plasma reactor corresponding to that of FIG. 48A with the exception that the plasma is isolated axially rather than laterally relative to the wafer pedestal.

FIG. 48C illustrates an embodiment corresponding to FIG. 48A but employing frequency isolation.

FIG. 49 is a cut-away side view of a plasma reactor corresponding to that of FIG. 48A with the exception that the all-semiconductor enclosure is monolithic.

FIG. 50 is a cut-away side view of a plasma reactor corresponding to that of FIG. 48A with the exception that the semiconductor enclosure is divided into a disk center section and an annular section having cylindrical skirt.

FIG. 51 is a cut-away side view of a plasma reactor corresponding to that of FIG. 48A with the exception that the semiconductor enclosure is divided into a disk center section, an annular side section and a separate cylindrical skirt.

FIG. 52 illustrates the plasma reactor of FIG. 50 with separate inner and outer induction coils.

FIG. 53 illustrates the plasma reactor of FIG. 51 with separate inner and outer induction coils.

FIG. 54 illustrates the plasma reactor of FIG. 48A with a cylindrical induction coil wound around the cylindrical skirt of the semiconductor enclosure.

FIG. 55 illustrates the plasma reactor of FIG. 49 with a cylindrical induction coil wound around the cylindrical skirt of the semiconductor enclosure.

FIG. 56 illustrates the plasma reactor of FIG. 50 with a cylindrical induction coil wound around the cylindrical skirt of the semiconductor enclosure.

FIG. 57 illustrates the plasma reactor of FIG. 51 with a cylindrical induction coil wound around the cylindrical skirt of the semiconductor enclosure.

FIG. 58 is a cut-away side view of a plasma reactor corresponding to that of FIG. 48A with the exception that the ceiling portion of the semiconductor enclosure is dome-shaped.

FIG. 59 is a cut-away side view of a plasma reactor corresponding to that of FIG. 49 with the exception that the ceiling portion of the semiconductor enclosure is dome-shaped.

FIG. 60 is a cut-away side view of a plasma reactor corresponding to that of FIG. 50 with the exception that the ceiling portion of the semiconductor enclosure is dome-shaped.

FIG. 61 is a cut-away side view of a plasma reactor corresponding to that of FIG. 51 with the exception that the ceiling portion of the semiconductor enclosure is dome-shaped.

FIG. 62 is a cut-away side view of a plasma reactor corresponding to that of FIG. 52 with the exception that the ceiling portion of the semiconductor enclosure is dome-shaped.

FIG. 63 is a cut-away side view of a plasma reactor corresponding to that of FIG. 53 with the exception that the ceiling portion of the semiconductor enclosure is dome-shaped.

FIG. 64 is a cut-away side view of a plasma reactor corresponding to that of FIG. 54 with the exception that the ceiling portion of the semiconductor enclosure is dome-shaped.

FIG. 65 is a cut-away side view of a plasma reactor corresponding to that of FIG. 55 with the exception that the

ceiling portion of the semiconductor enclosure is dome-shaped.

FIG. 66 is a cut-away side view of a plasma reactor corresponding to that of FIG. 56 with the exception that the ceiling portion of the semiconductor enclosure is dome-shaped.

FIG. 67 is a cut-away side view of a plasma reactor corresponding to that of FIG. 57 with the exception that the ceiling portion of the semiconductor enclosure is dome-shaped.

FIG. 68A is a diagram of a first version of the plasma confinement magnets optionally employed in the embodiments of FIGS. 48-67.

FIG. 68B is a diagram of a second version of the plasma confinement magnets optionally employed in the embodiments of FIGS. 48-67.

FIG. 68C is a diagram of a third version of the plasma confinement magnets optionally employed in the embodiments of FIGS. 48-67.

FIG. 68D is a diagram of a third version of the plasma confinement magnets optionally employed in the embodiments of FIGS. 48-67.

FIG. 68E is a diagram of a fourth version of the plasma confinement magnets optionally employed in the embodiments of FIGS. 48-67.

FIG. 69 is a cut-away side view of a plasma reactor of an alternative embodiment of the invention corresponding to that of FIG. 48A but employing capacitive coupling.

BEST MODES FOR CARRYING OUT THE INVENTION

Basic Concept of the Invention

Referring to FIG. 1, a plasma reactor includes a sealed cylindrical chamber 100 enclosed by a cylindrical side wall 105, a disk-shaped ceiling 110 and a base 115. A wafer pedestal 120 supports a semiconductor wafer or workpiece 125

to be processed by the reactor. The wafer pedestal 120 may be an electrostatic chuck assembly, as disclosed in co-pending U.S. Patent Application Serial No. 08/ , filed July 26, 1995 by Kenneth S. Collins et al. entitled "PLASMA SOURCE WITH AN ELECTRONICALLY VARIABLE DENSITY PROFILE" and assigned to the assignee of the present application, the disclosure of which is incorporated herein by reference. A bias RF power generator 130 applies a bias potential to the wafer pedestal 120 through an impedance match circuit 135 of the type well-known in the art. Impedance match circuits are disclosed, for example, in U.S. Patent No. 5,392,018 to Collins et al. and U.S. Patent No. 5,187,454 to Collins et al. Gas inlets 137 adjacent the pedestal 120 admit a processing gas such as an etchant precursor gas such as a C_xF_x gas. A vacuum pump 140 evacuates the chamber 100 to a desired pressure. An overhead inductive coil antenna 145 held over the ceiling 110 in an insulating antenna holder 147 is connected to a plasma source RF power generator 150 through another conventional impedance match circuit 155 and inductively couples RF power into the chamber through the ceiling 110.

In order to provide a uniform ground return for the bias RF power over the entire surface of the wafer 125 and in order to minimize current flow toward the side wall 105, the ceiling 110 is grounded. However, this feature requires the ceiling 110 to perform two functions: (a) act as a conductor that can be grounded and (b) act as a non-conductor so that the RF induction field from the overhead coil antenna 145 can pass therethrough. In order to fulfill its dual-function role, the ceiling 110 is a semiconductor such as silicon. The silicon ceiling 110 may be insulated from conductive member of the chamber by insulators 158. It is felt that the silicon ceiling 110, as a semiconductor, has sufficient conductive properties to act as an electrode or ground plane. In order to vertically confine the plasma

closer to the wafer 125 and bring the uniform overhead ground plane into closer proximity to the wafer 125 (i.e., closer than the side wall 105) to minimize sideways plasma current flow to the side wall 105, the silicon ceiling 110 preferably is placed within a distance of the wafer 125 less than the wafer diameter and as close as only a fraction of the wafer diameter (e.g, within a few centimeters for a 20 cm diameter wafer). This distance can be as great as 20 cm and as little as 1 cm although a preferable range is 2-10 cm.

The ceiling 110 is a semiconductor window of a semiconductor material which is preferably silicon. However, other well-known semiconductor materials may be employed, such as silicon carbide, germanium, III-V compound semiconductors such as gallium arsenide or indium phosphide and II-III-V compound semiconductors such as mercury cadmium telluride. The requisite dopant impurity level at room temperature given a desired resistivity value of the silicon window electrode may be obtained from the graph of Fig. 4.14 of Grove, Physics of Semiconductors, page 113. The temperature of the silicon window 110 must be maintained within a range above which it does not act like a dielectric and below which it does not act like a conductor. The requisite temperature range may be obtained from the graph of Fig. 4.8 of Grove, Physics of Semiconductors illustrating the electron concentration in n-type silicon as a function of temperature. This graph shows that below about 100°K, the silicon begins to act like a dielectric while above about 600°K the silicon begins to act like a conductor. It is therefore preferable to maintain the temperature of the silicon ceiling 110 in a range where the carrier electron concentration is fairly constant with respect to temperature, which is within the range between 100°K and 600°K.

The advantages of the plasma reactor of FIG. 1 include the even distribution across the entire wafer surface of the plasma source power generated by the overhead coil antenna 145 in comparison with the conventional type of reactor having a coil wound around the side wall. Thus, plasma ion generation is not confined to the vicinity of the side wall but is uniformly distributed over the wafer surface. Plasma ion uniformity is enhanced because the grounded ceiling electrode 110 reduces or eliminates plasma current flow to the side wall 105, in contrast to the sideways current flow in the plasma reactor having an overhead coil antenna over a dielectric ceiling as disclosed in U.S. Patent No. 4,948,458 referred to above. Also, the close vertical proximity between wafer and ceiling reduces the distance between the wafer and the region in which plasma ions are generated, thereby reducing recombination losses and permitting the chamber pressure to be increased (e.g., to be in the range of 50-200 mTorr, for example). Such an increase in chamber pressure can be desirable for enhancing certain processing performance parameters, such as etch selectivity. The uniformity of plasma ion generation in the embodiment of FIG. 1 (achieved by the overhead coil antenna 145) coupled with the reduction in current flow to the chamber side wall (achieved with the grounded silicon ceiling 110 in close proximity to the wafer 125) reduces or eliminates differences in processing (e.g., etching) at the wafer center and processing at the wafer periphery, thereby widening the processing window. Specifically, the tendency to overetch or punch through at the wafer periphery is reduced while at the same time the tendency to etch stop at small feature sizes at the wafer center is also reduced. Also, the tendency near the wafer periphery to facet the photoresist mask edges and to generally etch the photoresist giving rise to poor etch profile is reduced or eliminated. Thus, the plasma reactor of FIG. 1 can provide at very small

feature sizes aggressive etch performance across the entire wafer surface with superior etch profile and superior etch selectivity with little or no microloading. Moreover, since there is little or no participation of the side wall 105, consumption of reactor components and the associated operating cost is significantly reduced. Accordingly, the invention provides a revolutionary advance in the art.

There are, however, a number of potential problems which, if not resolved, could render the reactor of FIG. 1 impractical. First, there is the problem of whether the silicon ceiling 110 will block the RF induction field of the overhead coil antenna 145 from ever reaching the chamber 100. For example, the impedance of the silicon ceiling 110 to the RF induction field may be too great to permit transmission therethrough. This may be affected by the dopant impurity concentration in the silicon ceiling 110 or by the temperature of the silicon ceiling 110. Alternatively, the RF induction field skin depth through the silicon ceiling 110 may not exceed the ceiling thickness, thus preventing transmission therethrough. Also, the RF induction field skin depth through the plasma in the chamber 100 may be greater than the chamber height (i.e., the wafer-top electrode gap), so that the RF induction power may not be efficiently coupled to the plasma. Another problem is that the close proximity of the ceiling 110 to the wafer 125 may be insufficient to separate the plasma sheath near the ceiling 110 from the plasma sheath near the underlying wafer 125, thereby shorting out the plasma from top to bottom. Also, insertion of the silicon material of the ceiling 110 into the RF return path of the bias RF power generator 130 may occasion significant RF bias power losses. Finally, there may not exist a suitable or practical range of resistivity values for the semiconductor window within which an RF inductive field can be coupled without undue loss or

attenuation. These problems are solved or otherwise disposed of in the analyses that follows immediately below.

The Induction Field's Skin Depth Through the Plasma is Sufficiently Short so that Power is Efficiently Absorbed in the Plasma:

The skin depth of the RF induction field from the overhead coil antenna 145 is less than the ceiling-to-wafer height (e.g., on the order of the wafer diameter or less), so that the power from the coil antenna 145 is inductively coupled to the plasma efficiently. This may be shown for two cases, namely a collisional skin depth in which the plasma source RF angular frequency is much less than the plasma momentum transfer elastic collision frequency, and a collisionless skin depth in which the plasma source RF angular frequency is much greater than the plasma momentum transfer elastic collision frequency.

The collisional skin depth δ_c of the RF induction field through the plasma is computed as follows:

$$(1) \quad \delta_c = (2\tau_m/\omega)^{1/2} c [(e^2 n_e)/(\epsilon_0 m_e)]^{-1/2},$$

where:

$\tau_m = 1.4 \cdot 10^7 \text{ sec}^{-1}$ is the electron-to-neutral momentum transfer collision frequency for an Argon plasma at a temperature of 300°K and a chamber pressure of 5mTorr,

$\omega = 12.57 \cdot 10^6 \text{ radians/sec}$ is the angular frequency of the induction field RF power source applied to the coil antenna,

$c = 3 \cdot 10^8 \text{ meters/sec}$ is the speed of light,

$e = 1.6022 \cdot 10^{-19} \text{ coulomb}$ is the electron charge,

$n_e = 5 \cdot 10^{17} \text{ meters}^{-3}$ is the applicable electron density,

$\epsilon_0 = 8.85 \cdot 10^{-12} \text{ farads/meter}$ is the electrical permittivity of free space, and

$m_e = 9.1095 \cdot 10^{-31} \text{ kg}$ is the electron mass.

Substituting the foregoing values into Equation 1 yields:

$$(2) \quad \delta_c = 1.1 \text{ cm}$$

as the collisional skin depth.

5 The collisionless skin depth δ_p of the RF induction field through the plasma is computed as follows:

$$(3) \quad \delta_p = c[(e^2 n_e)/(\epsilon_0 m_e)]^{-1/2}.$$

Substituting the foregoing values into Equation 3 yields:

$$(4) \quad \delta_p = 0.8 \text{ cm}$$

10 as the collisionless skin depth. Thus, in either case the skin depth of the RF induction field is significantly less than the wafer-to-ceiling height, so that the RF source power is efficiently absorbed by the plasma.

15 The Induction Field's Skin Depth Through the Silicon Ceiling is Greater Than the Ceiling Thickness, So That It Can Extend Through the Ceiling

The RF induction field of the coil antenna 145 has a skin depth in silicon that far exceeds the one-inch (2.54 cm) thickness of the silicon ceiling. Therefore, the RF induction field is sufficiently deep to penetrate the silicon ceiling 110, provided the resistive losses are sufficiently small. This may be closely estimated by computing the skin depth δ of a uniform plane wave incident on an infinite planar silicon slab:

$$25 \quad \delta = [\pi f \sigma \mu]^{-1/2},$$

where:

$f = 2 \text{ MHz}$ is the frequency of the RF power source 130 connected to the coil antenna 145,

30 $\mu = 4\pi \cdot 10^{-7} \text{ Henries/meter}$ is the magnetic permeability of the silicon slab, and

$\sigma = 3.33 \Omega^{-1} \text{meters}^{-1}$ is the conductance of the 30 Ω -cm resistivity silicon slab.

Substituting the foregoing values into the equation for δ yields:

$$35 \quad \delta = 0.195 \text{ m},$$

so that the skin depth is about eight times the thickness of the silicon ceiling 110 and therefore the RF induction field has a penetration depth well into the chamber 10, provided the silicon ceiling 110 does not pose a high impedance to the RF induction field.

The Silicon Ceiling Poses a Low Impedance to the RF Induction Field:

Transmission of an RF induction field through an embodiment of the silicon ceiling 110 consisting of a disc-shaped silicon slab of 30 Ω -cm resistivity at room temperature measuring 13.5 inches in diameter and 1 inch in thickness was tested at room temperature by placing induction coils on opposite sides of the slab, connected the coil on one side of the slab to a variable frequency RF source and connecting the coil on the other side to a multichannel analyzer and then sweeping the frequency of the RF source from 1 kHz to 10 MHz. The resulting output of the multichannel analyzer is illustrated in FIG. 2. For the curve labelled "magnitude", the vertical axis is the ratio of the magnitudes of the received and transmitted signals and extends from a value of unity at the top of the scale and falls in 0.1 unitless increments, while the horizontal axis is frequency and extends from 1 kHz on the left to 10 MHz on the right. For the curve labelled "phase", the vertical axis is the difference between the phase angles of the received and transmitted signals and extends from a value of 20° at the top of the scale and falls in 20° increments. The graph of FIG. 2 clearly indicates that there virtually is no loss of RF power through the silicon slab out to 2 MHz and that there is relatively little loss above 2 MHz.

While FIG. 2 illustrates the results obtained with a discoid silicon slab, FIG. 3 illustrates results obtained at room temperature with a cylindrical silicon slab having a

12.3 inch outside diameter, a 1 cm wall thickness. A 5-turn transmission coil was wound around the outside of the cylindrical slab for transmitting RF power into the interior volume surrounded by the cylindrical silicon slab.

5 Measurements were taken at the center of the interior volume from an 8-turn receiver coil having a 2.3 inch outside diameter and a 3 inch length. For the curve labelled "magnitude", the vertical axis is the ratio of the magnitudes of the received and transmitted signals and
10 extends from a value of unity at the top of the scale and falls in 0.1 unitless increments, while the horizontal axis is frequency and extends from 1 kHz on the left to 10 MHz on the right. For the curve labelled "phase", the vertical axis is the difference between the phase angles of the
15 received and transmitted signals and extends from a value of 0° at the top of the scale and falls in 20° increments. The graph of FIG. 2 clearly indicates that there virtually is no loss of RF power through the silicon slab out to 2 MHz and that there is relatively little loss above 2 MHz. Thus, the
20 silicon ceiling 110 is nearly transparent to the RF induction field.

The Silicon Ceiling Poses a Low Impedance to the RF Induction Field Over A Wide Temperature Range

25 The tests described above with reference to FIGS. 2 and 3 were repeated at silicon temperatures of 200° and 250° and similar results were obtained, demonstrating that the temperature of the silicon ceiling 110 may be varied over a wide range to adjust the polymerization and fluorine
30 scavenging processes as desired. However, at temperatures well above 300°C the silicon ceiling 110 becomes intrinsic and therefore cuts off the RF induction field of the overhead coil antenna 145 from reaching the chamber 100. It is preferable to employ a high resistivity silicon (e.g., 30
35 Ω-cm at room temperature) in the ceiling 110. Otherwise,

using, for example, 0.01 Ω -cm resistivity silicon in the ceiling 110 would require reducing the frequency of the RF induction field to the kHz range or below in order to couple through the silicon ceiling. Another option is to reduce the ceiling thickness.

The Silicon Ceiling Adds Virtually No Losses in the Return Path of the Bias RF Power Source

That the RF power loss occasioned by insertion of the silicon ceiling 110 in the RF return path for the bias power generator 130 is low may be seen by computing the resistance of a silicon slab to a current flux normal to the slab's flat surface assuming a skin depth much greater than the slab thickness and assuming the presence of a perfect conductor ground plane on the back of the silicon slab. This resistance is shown to be far less than the measured driving point RF impedance at the wafer pedestal 120, so that the insertion of the silicon ceiling causes only a fractional increase in the overall bias RF power loss.

The resistance R_{slab} of the silicon slab to a current flux normal to the surface is computed as follows:

$$R_{\text{slab}} = \Gamma t (d/2)^{-2} / \pi,$$

where:

$t = 0.0254$ m is the slab thickness,

$d = 0.318$ m is the slab effective diameter exposed to the current flux, and

$\Gamma = 0.30$ Ω -m is the resistivity of the 30 Ω -cm resistivity silicon at room temperature.

Substituting the foregoing values into the equation for R_{slab} yields for the slab resistance:

$$R_{\text{slab}} = 0.096 \Omega.$$

The driving point impedance Z at the wafer pedestal 120 has been measured in typical parallel electrode plasma reactor of the type illustrated in FIG. 1 (with a 2.0 MHz plasma power source RF induction field from a coil antenna

and an applied RF bias on the pedestal of 1.8 MHz) as 38.7Ω at an angle of 50.1° . The real part of this driving point impedance is:

$$\text{Re}(Z) = 38.7 \Omega \cos(50.1^\circ (180/\pi)) \approx 24 \Omega.$$

5 The fractional increase in RF power loss occasioned by the insertion of the silicon ceiling is:

$$R_{\text{slab}}/\text{Re}(z) = 0.096/24 = 0.004,$$

which is a very small fraction. Thus, the insertion of a silicon slab into the RF return path of the RF bias power generator 130 adds only a negligible amount of resistance.

The Plasma DC Sheath Thickness is Sufficiently Short to Avoid Shorting Between the Ceiling and the Wafer

15 There is a sheath at the edge of the plasma across which the ion density falls from the plasma ion density value to zero. If the sheath at the wafer surface meets the sheath at the chamber ceiling, there is no plasma in the chamber. The high voltage plasma DC sheath thickness, s , is computed as follows:

$$20 \quad s = (2^{1/2}/3) [(\epsilon_0 \cdot T_e)/(e \cdot n_e)]^{1/2} (2 \cdot V_0/T_e)^{3/4},$$

where:

$\epsilon_0 = 8.85 \cdot 10^{-14}$ farads/cm is the electrical permittivity of free space,

25 $T_e = 5$ eV is the mean electron temperature assuming a Maxwellian distribution,

$e = 1.6022 \cdot 10^{-19}$ coulombs is the electron charge,

$n_e = 5 \cdot 10^{11} \text{ cm}^{-3}$ is the average electron density in the bulk plasma adjacent the sheath, and

30 $V_0 = 300$ Volts is the DC voltage across the plasma sheath. Substituting the foregoing values into the equation for s yields:

$$s = 0.04 \text{ cm},$$

35 so that the plasma sheath thickness is only a small fraction of the wafer-to-ceiling distance and therefore there is no risk of the top and bottom sheaths intersecting.

There is a wide range of resistivity values for a semiconductor window electrode through which RF power may be coupled with low attenuation losses:

5 In order to ascertain a range of resistivity values of a semiconductor window through which an inductive RF field is to be coupled or transmitted with low attenuation losses, a thickness of the window must be selected, the frequency of the RF inductive field must be selected and a minimum ratio

10 of RF skin depth to window thickness must be specified. In a first example, the window thickness is $T = 0.0254$ meter, the RF frequency f is $2 \cdot 10^6 \text{ s}^{-1}$ and the minimum ratio of RF skin depth to window thickness is $r = 5$. For this first example, the minimum resistivity for the semiconductor window is calculated assuming:

15 $\mu = 4\pi \cdot 10^{-7}$ Henries/meter is the magnetic permeability of the semiconductor window,

$S = r \cdot T$ is the skin depth of the RF induction field in the semiconductor window. The minimum resistivity Γ_{\min} is then computed by the following equation:

20
$$\Gamma_{\min} = S^2 \cdot \pi \cdot f \cdot \mu$$

Substituting the values given above into this equation, the minimum resistivity for this first example is:

$$\Gamma_{\min} = 12.735 \text{ } \Omega\text{-cm.}$$

25 Next, the maximum resistivity must be computed for this first example. For purposes of the following analysis, it will be assumed that there is a ground plane transmissive to the RF induction field behind the semiconductor window. The real part of the RF bias plasma load impedance must be defined, the acceptable loss L must be defined and the effective plasma interaction diameter d of the semiconductor window must be defined. In this first example, the real

30 part R of the RF bias plasma impedance is:
 $R = -25$,
the acceptable loss (normalized at 100% = 1) is

35 $L = 0.01$,

the effective plasma interaction diameter of the semiconductor window is

$d = 0.318$, from which the effective plasma interaction area A is computed as $A = \pi (d/2)^2$.

5 The maximum resistivity Γ_{\max} is given by the following equation:

$$\Gamma_{\max} = L \cdot R \cdot A / T.$$

Substituting the foregoing values into this equation yields:

$$\Gamma_{\max} = 78.172 \text{ } \Omega\text{-cm.}$$

10 Therefore, in this first example, the resistivity of the semiconductor may lie anywhere within the range between $12.735 \text{ } \Omega\text{-cm}$ and $78.172 \text{ } \Omega\text{-cm}$.

In a second example, the semiconductor window thickness is reduced by a factor of ten so that $T = 0.00254$ meters.

15 In this case, Γ_{\min} is reduced to $0.127 \text{ } \Omega\text{-cm}$, while Γ_{\max} increases to $781.719 \text{ } \Omega\text{-cm}$.

In a third example, the parameters of the second example are repeated except that the frequency of the RF induction field is reduced to 100 kHz ($f = 0.1 \cdot 10^6 \text{ s}^{-1}$). In this case, Γ_{\min} is reduced to $0.006 \text{ } \Omega\text{-cm}$, while Γ_{\max} is unchanged (from the second example) at $781.719 \text{ } \Omega\text{-cm}$.

20 In a fourth example, the parameters of the first example are adopted except that the frequency of the RF induction field is increased to 10 MHz ($f = 10 \cdot 10^6 \text{ s}^{-1}$). In this case, Γ_{\min} is increased to $63.675 \text{ } \Omega\text{-cm}$, while Γ_{\max} is decreased to $78.172 \text{ } \Omega\text{-cm}$, thus narrowing the range somewhat relative to the other examples.

25 Thus, the useful range of resistivity values is broad. If the semiconductor window is a 2.54 cm -thick silicon slab and the RF frequency of the induction field is 2 MHz , then the preferred resistivity is $30 \text{ } \Omega\text{-cm}$.

Other Preferred Embodiments of the Invention

While the silicon ceiling 110 is grounded in the preferred embodiment of FIG. 1, in the embodiment FIG. 4 power from the RF generator 130 is split by a power splitter 160 between the pedestal 120 and the silicon ceiling 110.

5 In order to provide a ground return path, the side wall 105 may be a grounded conductor. In FIG. 5, the silicon ceiling 110 is driven independently from the wafer pedestal 120 by a separate RF power generator 165 through a conventional impedance match circuit 170. While the embodiment of FIG. 1

10 employs a single coil as the inductor antenna 145, in the embodiment of FIG. 6 the inductor antenna 145 is comprised of plural (in this case, two) independently driven coils, namely an inner coil 175 overlying the wafer center and an outer coil 180 overlying the wafer periphery. In the

15 implementation of FIG. 6, the inner and outer coils 175, 180 are planar concentric coils driven by separate plasma source power generators 185, 190. The advantage is that plasma variations along the radius of the chamber 100 can be compensated by selecting different power levels from the two

20 RF generators 185, 190. In a prototype of the embodiment of FIG. 6, the inner and outer coils consisted of nine turns each. A fixed impedance match was realized using parallel and series capacitors 195, 200 connected to the input and return ends, respectively, of the inner coil 175 and

25 parallel and series capacitors 205, 210 connected to the input and return ends, respectively, of the outer coil 180.

In a working example, the plasma source RF power generator 155 produced 2600 Watts at 2.0 MHz, the bias RF

30 power generator 130 produced 1600 Watts at 1.8 MHz, C_2F_6 gas was pumped into the chamber 100 at a rate of 30 sccm with 100 cc of Argon, the chamber pressure was maintained at 6.5 mTorr and the temperature of the silicon ceiling 110 was maintained at 200° C. Under these conditions, the parallel

35 and series capacitors 195, 200 of the inner coil 175 had

capacitances of 8.19699 nanoFarads and 2.12631 nanoFarads, respectively, while the parallel and series capacitors 205, 210 of the outer coil 180 had capacitances of 4.45572 nanoFarads and 1.09085 nanoFarads, respectively. By shorting one of the inner and outer coils 175, 180, the input impedance of the other could be measured. Indeed, with the foregoing capacitances being selected, the complex impedance of the inner coil 175 was measured as 51Ω at a complex plane angle of -12° and the complex impedance of the outer coil 180 was measured as 51.8Ω at a complex plane angle of -8.6° . Thus, their impedance nearly matched the standard 50Ω output of the RF generators 185 and 190.

In the embodiment of FIG. 7, the side wall 105 is replaced by a silicon side wall 215 and inductive coupling is provided by a coil inductor 220 wound around the exterior of the silicon side wall 215 and connected to the plasma source power generator 150' through the impedance match circuit 155'. In FIG. 7, the silicon side wall 215 is grounded. As in the embodiment of FIG. 4, FIG. 8 illustrates that the power splitter 160 may split RF power from the bias generator 130 between the pedestal 120 and the silicon side wall 215. As in the embodiment of FIG. 5, FIG. 9 shows how the silicon side wall 215 may be independently powered by the separated RF generator 165 through the match circuit 170. FIG. 10 shows how the silicon ceiling 110 and overhead coil antenna 145 of FIG. 1 may be combined with the silicon side wall 215 and side coil antenna 220 of FIG. 7. FIG. 11 illustrates how the power splitter 160 of FIG. 8 may be employed in the embodiment of FIG. 10 to split power from the bias generator 130 between the side wall 215 and the pedestal 120. FIG. 12 illustrates the combination of the embodiment of FIG. 9 with the overhead coil antenna 145 and silicon ceiling 110 of FIG. 1.

FIGS. 13A, 13B, 13C and 13D illustrate modifications of the embodiments of FIGS. 1, 4, 5 and 6, respectively, in

which the planar silicon ceiling 110 and planar inductive coil antenna 145 have been replaced by a dome-shaped silicon ceiling 230 and a dome-shaped coil antenna 235, respectively. In one implementation, the dome-shaped coil antenna 235 is wound in a helix. FIG. 14 illustrates an embodiment in which the dome-shaped coil antenna 235 extends from near the top of the dome-shaped ceiling 230 and past the bottom of the dome-shaped ceiling 230 to wind around the side wall 105. In this case, at least that portion of the side wall 105 surrounded by the bottom portion of the coil antenna 235 would have to be a non-conductor such as quartz or a semiconductor such as silicon. FIG. 15 illustrates an embodiment corresponding to that of FIG. 10 in which the flat silicon ceiling 110 and the flat coil antenna 145 are replaced by the dome-shaped silicon ceiling 230 and the dome-shaped coil antenna 235 of FIG. 13A.

FIG. 16 illustrates how a power splitter 250 can be employed to split power from the plasma source RF power generator 150 between the inner and outer coil antennas 175, 180 overlying the silicon ceiling 110 of FIG. 6. An RF power splitter is disclosed in U.S. Patent No. 5,349,313 to Collins et al. As disclosed in the co-pending Collins et al. patent application incorporated by reference above, a controller 260 can vary the power ratio between the inner and outer coil antennas 175, 180 to compensate for any difference between the plasma ion densities over the wafer center and the plasma ion density over the wafer periphery. FIG. 17A illustrates an embodiment corresponding to that of FIG. 15 in which the power splitter 250 splits RF power from the plasma source power generator 150 between the side coil 220 and the dome-shaped overhead coil 235. FIG. 17B illustrates an embodiment with the dome-shaped silicon ceiling 230 having an inner (upper) dome-shaped coil 270 and an outer (lower) dome-shaped coil 280. The power splitter 250 splits RF power from the plasma source power generator

150 between the inner and outer dome-shaped coils 270, 280. The silicon ceiling 230 and the wafer pedestal 120 of FIG. 17B may be connected in accordance with any one of the embodiments of FIGS. 13A, 13B or 13C. FIG. 18 shows how the power splitter 250 can split power from the plasma source RF power generator 150 between the overhead coil antenna 145 and the side coil antenna 220 of FIG. 10.

FIG. 19 illustrates how the power splitter 250 can split power from the plasma source RF generator 150 between the overhead coil antenna 145 and the silicon ceiling 110. In the embodiment of FIG. 19, the wafer pedestal 120 can either be grounded or connected to the bias RF power generator 130 through the impedance match circuit 135. FIG. 20 illustrates how the power splitter 250 can split power from the RF generator 150 between the overhead coil antenna 145 and the wafer pedestal 120. In the embodiment of FIG. 20, the silicon ceiling 110 can either be grounded or can be connected to the separate RF power generator 165 through the match circuit 170. FIG. 21 is an embodiment corresponding to that of FIG. 19 but employing the dome-shaped silicon ceiling 230 and the dome-shaped coil antenna 235 in lieu of the flat silicon ceiling 110 and the planar coil antenna 145 of FIG. 19. FIG. 22 is an embodiment corresponding to that of FIG. 20 but employing the dome-shaped silicon ceiling 230 and the dome-shaped coil antenna 235 in lieu of the flat silicon ceiling 110 and the planar coil antenna 145 of FIG. 20.

FIG. 23 illustrates an embodiment in which the silicon ceiling 110 and the wafer pedestal 120 are each the RF ground return for the other. The ceiling and pedestal 110, 120 are driven through respective impedance match circuits 280, 290 by respective independent RF power generators 300, 305 of respective RF frequencies f_1 and f_2 through respective RF isolation filters 310, 315 and are each connected to ground through respective ground RF filters

320, 325. The isolation filters 310, 315 prevent the RF energy from either one of the RF power generators 300, 305 from reaching the other. The ground RF filters 320, 325 permit each one of the ceiling and pedestal 110, 120 to return to ground the RF power radiated across the chamber 100 by the other. At the same time, the ground RF filters 320, 325 prevent the RF power applied to either one of the ceiling and pedestal 110, 120 from being shorted directly to ground. Specifically, the isolation filter 310 connected between the silicon ceiling 110 and the RF power generator 300 of frequency f_1 passes RF power at the frequency f_1 and blocks RF power at the frequency f_2 . The isolation filter 315 connected between the wafer pedestal 120 and the RF power generator 305 of frequency f_2 passes RF power at the frequency f_2 and blocks RF power at the frequency f_1 . The ground filter 320 connected between the silicon ceiling 110 and ground passes RF power at the frequency f_2 and blocks RF power at the frequency f_1 . The ground filter 325 connected between the wafer pedestal 120 and ground passes RF power at the frequency f_1 and blocks RF power at the frequency f_2 .

The impedance match circuits 280, 290 are of the conventional type discussed previously herein and employ voltage and current sensors or impedance match transducers (not shown) in the conventional manner to measure actual input impedance. In order to prevent the RF power from either one of the two RF generators 300, 305 from interfering with the operation of the impedance match circuit of the other, respective match isolation filters 330, 335 are connected between the impedance match transducers and the transducer inputs to the impedance match circuits 280, 290, respectively. The match isolation filter 330 at the input to the f_1 match circuit 280 passes RF power at the frequency f_1 and blocks RF power at the frequency f_2 . The match isolation filter 335 at the input to the f_2 match

circuit 290 passes RF power at the frequency f_2 and blocks RF power at the frequency f_1 .

5 The various RF filters 310, 315, 320, 325, 330, 335 may be constructed of passive reactive components (capacitors and inductors) using techniques well-known in the art. If the two frequencies f_1 , f_2 are widely separated (e.g., by an octave), then the various RF filters 310, 315, 320, 325, 330, 335 can be suitable high-pass and low-pass filters with the suitably selected cut-off frequencies. Otherwise, if 10 the two frequencies f_1 , f_2 are not sufficiently separated, then the various RF filters 310, 315, 320, 325, 330, 335 should be bandpass or band reject filters centered at the appropriate frequencies.

15 FIG. 24 illustrates an embodiment corresponding to that of FIG. 23 but employing the dome-shaped silicon ceiling 230 and dome-shaped coil antenna 235 of FIG. 13A in lieu of the flat silicon ceiling 110 and planar coil antenna 145 of FIG. 23.

20 FIG. 25A illustrates the use of a conductive backplane 400 on the upper side or back surface of the silicon ceiling 110. The electrical potential (e.g., ground or, alternatively, the output of an RF generator) to be applied to the silicon ceiling 110 is applied directly to the conductive backplane 400 for uniform distribution across the 25 back surface of the ceiling 110. The backplane 400 may be of any highly conductive material such as aluminum or copper, for example. Moreover, the backplane 400 must have sufficient openings or apertures to prevent the formation of eddy currents by the inductive RF field of the overhead coil antenna 145 which would block transmission of the RF 30 inductive field through the backplane 400. For example, the top view of FIG. 25B illustrates that the conductive backplane 400 may be in the shape of a star, with plural conductive arms 405 extending radially from a conductive 35 center 410. Preferably, the spaces or apertures 415 between

the conductive arms 405 are of a characteristic width on the order of the thickness of the silicon ceiling 110. This feature provides uniform current distribution and vertical current flow through the silicon ceiling 110. The center connected arms of the embodiment of FIG. 25B may be preferable in the case of silicon laminated on ceramic for ease of fabrication. FIG. 25C illustrates an alternative embodiment of the conductive backplane 400 which consists of an outer conductive annulus 420 with plural conductive arms 425 extending from the conductive annulus 420 radially inwardly toward an imaginary center point 430. The apertures 435 between the conductive arms 425 are of a characteristic width on the order of the thickness of the silicon ceiling 110, as shown in FIG. 25C. Preferably, electrical contact is made along the entire annulus 420. Preferably, the outer conductive annulus 420 is beyond the effective radial range of the RF inductive field.

Preferably, the silicon ceiling is about 1 inch (2.54 cm) thick for a 13 inch (32 cm) diameter wafer to provide structural integrity and an anti-implosion safety factor in excess of 10. However, to significantly reduce the thickness of the silicon ceiling (e.g., to a fraction of an inch), FIG. 26 illustrates how the silicon ceiling 110 and its backplane 400 may be bonded to a strong support substrate 500 such as a ceramic disk. The overhead inductive coil antenna holder 147 is placed over the substrate 500. In order to control the temperature of the silicon ceiling 110, a heater layer 510 is placed on top of the antenna holder 147 and a cooling plate 520 is placed on top of the heater layer 510. FIG. 27 illustrates how the role of the substrate 500 and the role of the antenna holder 147 may be merged into a single member by employing a strong material such as a ceramic in the antenna holder 147 and bonding the silicon ceiling 110 with its conductive backplane 400 directly to the antenna holder 147.

FIG. 28 illustrates an embodiment of the invention employing an alternative antenna holder 147' consisting of a conductor such as aluminum or copper, for example. In this embodiment, an insulating material 146 is provided between the windings of the inductive coil antenna 145 and the conductive antenna holder 147'. In order to prevent the inductive field of the coil antenna 145, each turn of the antenna 145 nests within a groove-shaped aperture 550 in the antenna holder 147', each aperture 550 opening to the bottom surface 147a of the conductive antenna holder 147'. The conductive antenna holder 147' of FIG. 28 may also serve as the conductive backplane for the silicon ceiling 110 as well as the strong supportive substrate for the ceiling 110, in which case the silicon ceiling 110 is bonded directly to the conductive antenna holder 147' of FIG. 28. However, a preferable option is to interpose the star-shaped conductive backplane 400 between the silicon ceiling 110 and the conductive backplane 147' of FIG. 28. FIG. 29 illustrates another embodiment of the conductive antenna holder 147' having a pair of wide concentric annular apertures 560, 565 in which respective ones of the inner and outer coil antennas 175, 180 of FIGS. 6 or 16 nest. The annular apertures 560, 565 open at the bottom surface 147a of the antenna holder so that there is no blockage of the RF induction field. In this embodiment, as FIG. 28, the conductive antenna holder can also serve as the conductive backplane for the silicon antenna (in lieu of the star-shaped conductive backplane 400) and as the strong supportive substrate for the silicon ceiling 110 (in lieu of the supportive substrate 500) and therefore may be bonded directly to the silicon ceiling 110. Preferably, however, the star-shaped conductive backplane is interposed between the conductive antenna holder 147' and the silicon ceiling

110 and is bonded with the silicon ceiling 110 to the antenna holder 147'.

The overhead coil antenna 145 has been described above as consisting of a single concentric spiral winding or of
5 inner and outer concentric spiral windings 175, 180. FIGS. 30A, 30B and 30C illustrate an alternative design of the overhead coil antenna 145 having non-concentric windings. Specifically, in FIG. 30A there is an outer circular conductor 600 which is of very low inductance and low
10 resistance so as to be at least nearly equipotential along its entire circumference. Plural spiral conductors 610 radiate inwardly in involute paths from the outer conductor 600 to a center point 620 joining all of the spiral conductors 610. Plasma source RF power (from the RF
15 generator 150) is applied between the outer conductor 600 and the center point 620. As illustrated in FIG. 30B, the involute spiral conductors 610 lie in a plane, while FIG. 30C illustrates an alternative embodiment for use with the dome-shaped ceiling 230 in which the involute spiral
20 conductors 610 form a dome. A dome shape, such as the dome shapes employed in the various embodiments disclosed in this specification may be non-linear or hemispherical or conical or a rotation of some arcuate curve such as a conical section or the combination of two different radii (as
25 disclosed earlier in this specification).

FIGS. 31A, 31B and 31C illustrate another non-concentric embodiment of the overhead coil antenna. FIG. 31B corresponds to the planar case while FIG. 31C corresponds to the dome-shaped case. An outer circular
30 conductor 700 has plural arcuate conductive arms 710 radiating inwardly therefrom terminating at ends 715A, 715B, 715C. A center point 720 has plural arcuate conductive arms 730 radiating outwardly therefrom and terminating at ends 740A, 740B, 740C. As employed in the embodiment of FIG. 16,
35 RF power from one output of the power splitter 250 of FIG.

16 is applied between the outer circular conductor 700 and the ends 715, while RF power from the other output of the power splitter 250 is applied between the center point 720 and the ends 740.

5 The conductor of the inductive antenna may follow any suitable three-dimensional path. For example, FIG. 32 illustrates a non-planar or 3-dimensional embodiment of the coil antenna 145 consisting of dual concentric cylindrical helical windings, namely an outer cylindrical helix 800 and
10 an inner cylindrical helix 810 all formed with the same conductor. FIG. 33 illustrates how a pair of dual concentric cylindrical helical windings of the type illustrated in FIG. 32, namely an inner dual concentric cylindrical helical winding 820 and an outer dual concentric
15 cylindrical helical winding 830 can be employed as the inner and outer windings of the overhead inductive antenna in the embodiment of FIG. 16, in lieu of the inner and outer planar windings 175, 180 of FIG. 16.

20 FIG. 34 illustrates another non-planar embodiment of the inductive antenna 145 of FIG. 1 consisting of stacked layers 840a, 840b, 840c of spiral windings 850.

 As mentioned previously herein, one factor that can give rise to plasma etch processing differences between the wafer center and the wafer periphery non-uniform etch
25 precursor gas distribution. Such non-uniformity in gas distribution arises from the introduction of the gas from the side of wafer pedestal through the gas inlets 137, so that there is relatively more etchant precursor gas near the wafer periphery and relatively less etchant precursor gas
30 near the wafer center. This problem is addressed in the embodiment of the silicon ceiling 110 of FIGS. 35A, 35B, 35C, 35D and 35E, which includes a center gas feed system built into the silicon ceiling 110 for introducing the etch precursor gas directly over the wafer in a symmetrical
35 manner relative to the wafer center.

Referring to FIG. 35D, the 1-inch thick silicon ceiling 110 has an approximately 0.33-inch deep 3.5-inch diameter counterbored opening 900 in its top surface. Preferably, as shown in FIG. 35E, about twenty-two symmetrically placed 0.20-inch diameter holes 910 are drilled down from the top surface of the counterbore opening 900 through about 80% of the thickness of the ceiling 110. Small 0.030-inch diameter holes 920 concentric with the larger holes 910 are laser-drilled from the bottom surface of the silicon ceiling 110. As shown in FIGS. 35A and 35B, a disk-shaped gas feed top 930 fits snugly within the counterbore opening 900 in the top surface of the silicon ceiling 110. The bottom surface of the gas feed top 930 has an approximately 0.01-inch deep 3.3-inch diameter counterbore opening 940 therein which forms a gas distribution manifold. A center gas feed pipe 950 passes through the center of the gas feed top 930 and opens into the counterbore opening 940. The bottom peripheral corner of the gas feed top has a step 960 cut out therein, the step 960 being 0.143-inch deep and extending 0.075-inch radially inwardly. The step 960 creates a circumferential pocket into which an annular teflon seal 970 having dimensions matching those of the step 960 snugly fits. Preferably, the teflon seal 970 has a U-shaped cross-section, as illustrated in FIG. 35C. An annular steel wire stiffener 975 within the teflon seal 970 provides stiffness for the seal 970.

The center gas feed silicon ceiling of FIGS. 35A-E can be employed as the silicon ceiling 110 in the embodiment of FIG. 16 in combination with the independently adjustable inner and outer inductive coil antennas 175, 180 controlled through the power splitter 250 by the electrical controller 260. The advantage is that the reactor's center-to-edge etch uniformity is enhanced by the uniform etchant precursor gas distribution across the wafer surface achieved with the center gas feed silicon ceiling 110 of FIGS. 35A-E, and any

residual center-to-edge etch non-uniformity can be precisely compensated by judiciously adjusting, using the controller 260, the relative proportion of power levels applied to the inner and outer coil antennas 175, 180 in the manner disclosed in the co-pending application of Collins et al. referred to above. As a result, the wafer center-to-edge etch uniformity is optimized to a degree not attainable in the prior art without sacrificing etch profile, etch selectivity and etch rate at very small feature sizes.

FIG. 36A illustrates another preferred embodiment of the center gas feed silicon ceiling which better protects the gas feed top from the plasma. In this embodiment, a shoulder 980 is provided along the circumferential edge of the counterbore opening 900 in the silicon ceiling 110. A silicon wafer 985 rests on the shoulder 980 and separates into two separate chambers the counterbore opening 900 in the top of the silicon ceiling 110 and the counterbore opening 940 in the bottom of the gas feed top 930. The silicon wafer 985 has plural gas feed holes 986 drilled therethrough which are all laterally displaced from the gas feed holes 910 in the silicon ceiling 110. The interposition of the silicon wafer 985 in this manner eliminates any direct-line path to the gas feed top 930 for plasma ions diffusing upwardly from the chamber through the holes 920. This feature better protects the top 930 from attack by the plasma. The top 930 is either a material such as a semiconductor or a dielectric which does not appreciably attenuate the RF inductive field, or, if its diameter is less than the diameter of the center null of the inductive antenna, may be a conductor such as stainless steel.

In the embodiments of FIGS. 35A-E and 36A, the gas feed holes 910, 920 are grouped about the center of the ceiling 110. However, in either embodiment the holes 910, 920 may be distributed from the center out to the periphery, if

desired, or may be grouped about the periphery instead of the center. This is illustrated in FIG. 36B, in which the gas feed holes 910, 920 are distributed about the periphery of the ceiling 110.

5 FIG. 37A illustrates a modification applicable to any of the embodiments employing a flat silicon ceiling 110, such as, for example, the embodiment of FIG. 1, in which an insulated grounded Faraday shield 990 is interposed between the overhead inductive antenna 145 and the silicon ceiling
10 110. The Faraday shield is of the conventional type whose shape is best shown in the top view of FIG. 37B and is used to reduce capacitive coupling from the inductive antenna 145 to the plasma. FIG. 38A illustrates a modification applicable to any of the embodiments employing a dome-shaped
15 silicon ceiling 230, such as, for example, the embodiment of FIG. 13A, in which an insulated grounded Faraday shield 990 is interposed between the overhead inductive antenna 145 and the silicon ceiling 230. FIG. 38B illustrates an embodiment corresponding to the embodiments of FIGS. 7-9 having a
20 cylindrical side semiconductor window electrode 215 and a cylindrical side inductive antenna 220, with the additional feature of a cylindrical Faraday shield 990' interposed between the inductive antenna 220 and the cylindrical semiconductor window electrode 215.

25 FIG. 39A is a proportional drawing illustrating a preferred arrangement of the elements described previously herein in a plasma etch reactor. FIG. 39B is a cross-section of a tube-shaped conductor employed in implementing the overhead inductive antenna, the interior volume of the
30 tube being used to pump a coolant such as water.

Each of the foregoing embodiments has been described as employing an electrical connection of the semiconductor window to an electrical potential such as an RF power source or ground, thereby employing the semiconductor window as an
35 electrode. However, such an electrical connection and the

use of the semiconductor window as an electrode is not necessary. In fact, the semiconductor window may be allowed to float electrically and left unconnected, rather than being employed as an electrode. It would nevertheless provide certain advantages even though not necessarily functioning as an electrode. One advantage is that the semiconductor material (e.g., silicon) of the semiconductor window is less liable to be a source of contamination, in comparison with other materials (e.g., quartz or aluminum) typically employed in or near the ceiling of a typical plasma reactor. Another advantage is that the semiconductor window is a scavenger for fluorine. Thus, the semiconductor window can function simultaneously both as a shield for the inductive antenna and as a scavenger for fluorine.

Any of the embodiments described above may be modified by placing both the semiconductor window electrode and its overlying coil inductor inside the chamber. In this modification, the semiconductor window electrode is not part of the chamber enclosure but rather rests under the ceiling of the enclosure. For a planar semiconductor window electrode of the type employed in the embodiments of FIGS. 1, 4-12, 16, 18-20, 23 and 37A, FIG. 40 illustrates the planar semiconductor window electrode 110 and the planar inductive antenna 145 inside the chamber 100 under and separate from a chamber ceiling 106. For a curved or dome-shaped semiconductor window electrode of the type employed in the embodiments of FIGS. 13A-15, 17A, 17B, 21, 22, 24 and 38, FIG. 41 illustrates the dome-shaped semiconductor window electrode 230 and the conformal inductive antenna 235 inside the chamber 100 under the chamber ceiling 106. For a cylindrical semiconductor window as employed in the embodiments of FIGS. 7-9, FIG. 41B illustrates a cylindrical semiconductor window 230' and cylindrical inductive antenna 235' inside the chamber 100.

While the semiconductor window of each of the foregoing embodiments has been illustrated as a monolithic structure, in accordance with one modification the semiconductor window may be segmented into plural members. Specifically, in
5 FIGS. 42 and 43 the planar semiconductor window 110' (corresponding to the planar semiconductor window electrode 110 of FIGS. 1 or 40, for example) is comprised of a center disk 110a and a peripheral annulus 110b surrounding and concentric with the disk 110a. Preferably, the disk 110a
10 and annulus 110b are of the same semiconductor material such as silicon or any one of the other exemplary semiconductor materials suggested above. In one embodiment, the relative center-to-edge etch performance is adjusted by applying different levels of RF power to the annulus 110a and disk
15 110b as desired. This is best accomplished by employing a single RF source 150 feeding an RF power splitter 160 having respective RF power outputs applied to the disk 110a and annulus 110b. This requires a third terminal (e.g., a grounded electrode) such as conductive side wall connected
20 to RF ground (not shown in FIG. 42). If, for example, the etch rate near the center of the wafer were greater than at that near wafer periphery, the RF power splitter 160 could be adjusted to apply more RF power to the center disk 110a and relatively less to the peripheral annulus 110b of the
25 semiconductor window. Moreover, for even greater control over the center-to-edge etch performance, the split inner and outer inductive antenna sections of FIGS. 6, 13D, 16 or 17B may be combined with the split semiconductor window electrodes 110a, 110b. Specifically, FIG. 42 illustrates
30 the inner and outer inductive antennas 175, 180 of FIG. 16 combined with the inner disk 110a and outer annulus 110b of the semiconductor window electrode. As in FIG. 16, the power splitter 250 has separate RF power outputs connected to respective ones of the inner and outer inductive antennas
35 175, 180.

FIG. 44 illustrates an embodiment corresponding to FIG. 42 in which the split semiconductor window electrode is arcuate or dome-shaped. In FIG. 44, the semiconductor window electrode center disk 110a corresponds to the center portion of a dome while the semiconductor window electrode peripheral annulus 110b corresponds to the outer portion of a dome and a contiguous cylinder at the circumferential base of the dome. FIG. 45 illustrates a modification of the embodiment of FIG. 44 in which the curvature of the dome nearly disappears so that the center disk 110a is virtually planar while the annulus 110b is virtually a cylindrical side wall.

While the third terminal requisite for the RF power splitting of FIGS. 42-45 has been described as a grounded side wall, in accordance with another modification the third terminal may be the semiconductor window peripheral annulus 110b while the RF power is split between the semiconductor window center disk 110a and some other entity such as the wafer pedestal 120. FIGS. 46 and 47 illustrate how this latter modification changes the embodiments of FIGS. 42 and 44, respectively. Such a modification carried out on the embodiment of FIG. 45 results in an embodiment corresponding to that of FIG. 13B. In the embodiments of FIGS. 46 and 47, the RF power splitter 250 has one of its RF power outputs connected to the semiconductor window center disk 110a and its other output connected to the wafer pedestal 120, while the semiconductor window peripheral annulus 110b is grounded.

The effective plasma interaction area of the semiconductor window may be changed to change the ratio of the effective plasma interaction areas of the semiconductor window and the wafer/wafer pedestal. There are three regimes for this area ratio:

(1) Symmetrical: the effective plasma interaction areas are about the same (the area ratio being about 1), so that

both the wafer and the semiconductor window electrode have the same plasma RF current density and the same RF and DC sheath voltage magnitudes;

(2) Not fully assymetrical: the area ratio lies in a range from 1 to a factor between 2 and 4, so that the current density and RF and DC sheath voltage magnitudes at the smaller area electrode are greater than at the larger area electrode and change significantly with further increases in the area ratio;

(3) Fully assymetrical: the area ratio exceeds a factor between 2 and 4 and the current density and RF and DC sheath voltage magnitudes do not change significantly with further increases in the area ratio, a saturation condition having been reached.

In the last case (i.e., case 3), the greater sheath voltage drop and RF current density appears at either the semiconductor window electrode or the wafer/wafer pedestal, whichever one has the smaller effective plasma interaction area. Raising the RF current density and sheath voltage drop in this manner has the same effect as raising the RF bias applied to one element (semiconductor window or wafer/pedestal) whose interaction area was reduced. As for the semiconductor window, such a change affects the rate of sputtering of scavenger material into the plasma and affects the rate of polymerization on the surface of the semiconductor electrode. As for the wafer/pedestal, such a change affects processing parameters normally affected by changes in applied bias RF power such as etch rate, etch profile and etch selectivity, for example.

The same principles apply when adjusting the ratio of effective plasma interaction areas in reactors having more than two electrodes. For example, in the embodiment of FIGS. 23 and 24, there are, in effect, four electrodes reduced to two by using electrodes which drive at one frequency and ground at another. Each pair of drive/ground

electrodes is analyzed separately, with the change area ratio having the same effects as outlined in the previous paragraph. As another example, in embodiments such as FIG. 4-12 in which a third electrode such as the cylindrical side wall is connected to a potential such as ground or another RF source, the same analysis applies, except that the apportionment of the ground return current between the grounded electrode (e.g., the cylindrical side wall) and the other terminal connected to an RF power source is determined by dynamic factors such as the phase difference between the two driven terminals as well as the effective plasma interaction area ratio. In order to maintain a constant predetermined phase difference between the two RF-driven electrodes, the invention disclosed in U.S. Patent No. 5,349,313 by Kenneth S. Collins et al. may be employed.

The ability to establish a desired phase relationship between a pair of RF-driven elements (electrodes or inductive antennas) may be employed to apportion RF power thereto. For example, in the embodiments such as FIGS. 16, 17A, 17B and 18 employing segmented inductive antenna portions, power apportionment as between the two segmented antenna portions is described above as being accomplished by varying the magnitudes of the RF voltages applied to the respective antenna portions. However, power apportionment may also be changed by changing the phase angle between the RF voltages applied to the different antenna portions. Likewise, in the embodiments such as FIGS. 42-47 employing segmented semiconductor window portions, power apportionment as between the two segmented semiconductor window portions is described above as being accomplished by varying the magnitudes of the RF voltages applied to the respective semiconductor window portions. However, power apportionment may also be changed by changing the phase angle between the RF voltages applied to the different semiconductor window portions.

FIG. 48A illustrates a plasma reactor much like the embodiment of FIG. 1 except that the concept of an overhead semiconductor window electrode is expanded to a semiconductor skirt 1010 extending vertically downward from a disk-shaped semiconductor ceiling 1020, the skirt 1010 and ceiling 1020 being insulated from one another by a dielectric insulating ring 1022 and constituting an all-semiconductor enclosure confining plasma within a processing region 1035 of the reactor chamber. Like the embodiment of FIG. 1, a coil inductor 1040 overlies the semiconductor ceiling 1020. The skirt 1010 can be cylindrical. An optional annular semiconductor foot 1011 integrally formed with the skirt 1010 can extend radially inwardly from the bottom of the cylindrical skirt 1010. A collar 1050 extends from near the radially inward edge of the foot 1011 to near a wafer pedestal 1060 supporting a wafer 1065 being processed, leaving a meandering high aspect ratio gap 1051 therebetween. In a preferred implementation, the wafer pedestal 1060 comprises an electrostatic chuck. One purpose of the collar 1050 is to confine plasma escaping around the pedestal 1060 from the processing region 1035 to the pumping annulus 1070 to the narrow (high aspect ratio) gap or passageway 1051, so that the escaping ions recombine at the wall surfaces along the passageway before reaching the pumping annulus 1070. Another feature is that the collar 1050 provides an overlapping baffle structure so that the gap 1051 provides a meandering path and plasma ions escaping to the pumping annulus 1070 must follow the meandering path. This feature further enhances the recombination of escaping plasma ions inside the gap 1051.

A pumping annulus 1070 is coupled to the processing region 1035 through a wafer slit valve 1075 and is evacuated by a pump 1080. In order to reduce or prevent plasma leakage through the slit valve 1075, the slit valve 1075 has as high an aspect ratio as possible to provide the narrowest

possible opening, in order to enhance recombination of plasma ions on the interior surface of the slit valve 1075.

In the preferred embodiment of FIG. 48A, the semiconductor enclosure 1030 is the vacuum boundary of the chamber. Alternatively, such a semiconductor enclosure may be provided within a metallic vacuum enclosure so that the semiconductor enclosure itself is not the vacuum boundary. This latter alternative may be useful in embodiments of the invention implemented by retro-fitting existing prior art reactor chambers.

There are several advantages provided by the all-semiconductor processing chamber enclosure of FIG. 48A. One advantage is that the all-semiconductor surfaces enclosing the processing region 1035 need not be passivated by accumulated polymer but instead may be left bare during plasma processing. This is because interaction between the plasma and the semiconductor surfaces does not produce by-products harmful to the plasma processing of the wafer. Instead, by-products produced by interaction of the plasma with the semiconductor surfaces enclosing the processing region 1035 tend to be volatile and are readily pumped away by the pump 1080. Since there is no need to passivate the surfaces enclosing the processing region 1035, there is no need to interrupt reactor operation to clean these surfaces, a significant advantage.

There are two ways to prevent accumulation of polymer on the surfaces enclosing the processing region 1035. One is to maintain these surfaces above the polymer condensation temperature. For this purpose, the ceiling 1020 and skirt 1010 are formed of a relatively highly thermally conductive material such as a semiconductor. Alternatively, the material need not be a semiconductor but may be a dielectric such as silicon nitride, aluminum nitride, quartz or alumina, for example. In the preferred embodiment employing a semiconductor material, this material is silicon, although

other semiconductor materials such as silicon carbide may be employed. Silicon is preferred for plasma processes involving silicon chemistry (such as silicon dioxide etch, for example). This is because the silicon window 1030 etches very slowly in such processes relative to the etch rates on the wafer (about 3 Å silicon etched from the silicon enclosure surface for every 1 μ of silicon dioxide etched from the wafer). Thus, about 35,000 wafers may be processed before a significant amount of material (e.g., 1 mm) is etched from the silicon enclosure 1030. The permissible loss due to etching of thickness of the semiconductor enclosure 1030 is limited by to factors: (a) the thickness of the enclosure 1030 required for structure integrity, and (b) the change in thickness which appreciably changes RF coupling from the coil antenna into the chamber. It is believed that a less than 10% change in thickness will not produce an appreciable change in RF coupling sufficient to affect processing of the wafer if the guidelines for semiconductor material selection given above in this specification are followed.

For aluminum or polysilicon plasma etch processes, which involve chlorine chemistry, the silicon walls may etch too fast (depending upon how the basic plasma processing parameters are controlled) and therefore silicon or semiconductor materials are not optimum for such applications. However, a semiconductor material is not necessary in carrying out the invention (unless an electrical or RF potential is to be applied thereto), and any suitable durable non-semiconductor such as silicon nitride may be employed for the process region enclosure 1030.

In order to maintain the temperature of the semiconductor ceiling 1020 at a selected temperature (e.g., for preventing polymer deposition), a temperature control system employing either direct thermal contact or indirect

thermal contact may be employed. In the drawing, a temperature control system employing indirect thermal contact is illustrated and includes a heater layer 1110 on top of an insulating layer 1112 enclosing the coil inductor 1040 over the ceiling 1020 and a cold plate 1120 over the heater layer 1110 and separated therefrom by a thermal resistance air gap 1114. The heater layer 1110 contains a conventional electrical heating element (not shown in the drawing of FIG. 48A), while the cold plate 1120 has internal water cooling jackets 1122. The amount of cooling provided by the cold plate 1120 is more than sufficient to offset any plasma heating of the ceiling 1020 while the amount of heat that the heater layer 1110 is capable of providing is more than sufficient to offset the cooling from the cold plate 1120. A conventional temperature sensor/controller (not shown in the drawing of FIG. 48A) governs the amount of current flow in the resistive heating element of the heater layer 1110.

In order to maintain the temperature of the semiconductor skirt 1010 at a selected temperature (e.g., for preventing polymer deposition), a temperature control system employing either direct thermal contact or indirect thermal contact may be employed. In the drawing, a temperature control system employing direct thermal contact is illustrated and includes a heater ring 1110A surrounding and contacting the skirt 1010 through an optional insulating layer 1112A which is not necessarily required. A cold ring 1120a contacts the skirt 1010. An optional insulating layer may be placed between the cold ring 1120a and the skirt 1010. The heater ring 1110A contains a conventional electrical heating element 1110B, while the cold ring 1120A has internal water cooling jackets 1122A. The amount of cooling provided by the cold ring 1120A is more than sufficient to offset any plasma heating of the skirt 1010 while the amount of heat that the heater ring 1110A is

capable of providing is more than sufficient to offset the cooling from the cold ring 1120A. A conventional temperature sensor/controller (not shown in the drawing of FIG. 48A) governs the amount of current flow in the resistive heating element of the heater ring 1110A.

The second way of preventing polymer deposition on surfaces enclosing the processing region 1035 is to apply an RF potential to these surfaces of sufficient strength to enhance ion bombardment of these surfaces by ions from the plasma. The ion bombardment power must be sufficient to remove polymer from the surfaces faster than it is deposited. For this purpose, the disk-shaped ceiling 1020 and the cylindrical skirt 1010 must be sufficiently conductive to act as electrodes for the applied RF power. The ceiling 1020 and the skirt 1010 are preferably semiconductors. However, they preferably should not be metallic because metal exposed to the plasma in the processing region 1035 furnishes by-products which contaminate the chamber and wafer. Another reason that semiconductor material is preferred over conductive (metallic) material for the ceiling 1020 and skirt 1010 is that conductive material in the ceiling 1020 would prevent transmission through the ceiling 1020 of RF plasma source power from the coil inductor 1040.

In a preferred embodiment, the two ways of preventing polymer deposition (temperature control and a sputter-promoting applied RF potential on the window electrode) are combined. Application of an RF potential to the semiconductor enclosure 1030 which promotes ion bombardment or sputtering of the surface advantageously reduces the surface temperature necessary to prevent polymer accumulation on the surface. For example, the temperature may be reduced from about 265°C typically required in the prior art to prevent polymer accumulation to about 100°C at a sufficiently high bias voltage, so that the invention

allows the reactor to run cooler while still preventing polymer accumulation on surfaces within the processing region 1035. Conversely, raising of the surface temperature of the semiconductor enclosure 1030 advantageously reduces the ion bombardment power or sputtering necessary to prevent polymer accumulation on the surface. In one example, the RF power applied to the semiconductor ceiling 1020 was 500 Watts at 0.1 MHz, bias power applied to the wafer pedestal 1060 was 1400 Watts at 1.8 MHz, source power applied to the coil antenna 1040 was 3000 Watts at 2.0 MHz while the temperature of the semiconductor enclosure 1030 was held at 200°C. While an inductive antenna in the form of a coil antenna 1040 was employed in carrying out this exemplary embodiment of the invention, other antenna types may be employed, and the invention is not confined to the use of coil antennas.

As described above, plasma leakage at the wafer pedestal 1060 is prevented by providing, with the collar 1050, a high aspect-ratio opening and/or a meandering passage. Also, as noted above, the slit valve 1075 is a high aspect-ratio opening for the same purpose. Such high aspect ratio openings include not only the side wall-pedestal gap overlaid by the collar 1050 but other types of passages as well such as process gas injection orifices, which naturally block leakage of plasma ions. However, the slit valve 1075 is necessarily large enough to accommodate the semiconductor wafer 1065 and therefore is more susceptible to plasma ion leakage therethrough. In order to prevent leakage of the plasma from the processing region 1035 through large apertures such as the slit valve 1075, an optional feature of the invention includes plasma confinement magnets such as the magnet rings 2130, 2135 on opposite boundaries of the slit valve 1075 to establish magnetic flux lines across the slit valve opening. Plasma ions, electrons or charged particles, upon approaching the

slit valve 1075, experience an acceleration normal to the magnetic flux lines and normal to their velocity so that they are diverted from a path through the slit valve 1075 and instead impact the side wall of the slit valve so as to be eliminated by recombination before reaching the pumping annulus 1070. This reduces the probability of ion passage through the slit valve 1075, depending upon the magnetic flux density of the magnets 2130, 2135, the charge on the ions and particles, their mass and velocity. Using plural magnets has the advantage of maximizing magnetic flux across the aperture while minimizing magnetic flux penetration into the chamber toward the wafer 1065. Preferably, the magnets 2130, 2135 are sufficiently strong to affect the heavier ions of the plasma. For example, the magnets should produce a magnetic flux density across the aperture on the order of about 50 Gauss or more, depending upon electron energy in the plasma, plasma ion energy, plasma reactor chamber pressure and other plasma processing parameters. For example, a magnetic flux density between 100 Gauss and 200 Gauss across the aperture reduced ion saturation current at a location 2 cm beyond the magnets by about 75% over a reactor chamber pressure range between 5 mT and 100 mT, an electron density range between 1 and 5×10^{11} electrons per cubic centimeter. The magnets are preferably cooled to 100°C, or at least well-below their Curie temperature and are shielded from the plasma ions by, for example, encapsulation in a durable material (such as silicon nitride). Alternative arrangements of the magnets 2130, 2135 will be described below in this specification.

The magnets 2130, 2135 do not prevent charge-neutral radicals and particles, including charge-neutral polymer-forming particles, from passing through the slit valve 1075. Thus, polymer may accumulate in the pumping annulus 1070. In order to capture and control such polymers in the pumping annulus 1070, the interior surfaces of the pumping annulus

1070 are maintained at a temperature well-below the polymer condensation temperature in order to deposit onto the interior surfaces of the pumping annulus 1070 the polymer precursor material escaping through the slit valve 1075.

5 Preferably, the pumping annulus 1070 is covered with a removable cold liner 2150 such as aluminum, anodized aluminum or plasma-sprayed silicon on aluminum, thermally coupled to a cold sink 2155. The advantage of this feature is that polymer accumulated on the cold liner 2150 of the
10 pumping annulus 1070 remains undisturbed by plasma ions, is not subject to plasma heating and is not liable to be sputtered off to become a diffuse contaminant in the chamber 1030. Therefore, the polymer may be allowed to accumulate to a great thickness on the cold liner 2150 before creating
15 any risk of contamination of the chamber. As a result, the cold liner 2150 need not be periodically cleaned or replaced except at the most remote intervals, a significant advantage. The cold liner 2150 may not be required since the polymer deposition rate is so low that polymer
20 accumulated in the pumping annulus surfaces may not need to be removed more often than 30,000 to 40,000 wafers processed in the chamber.

In order to prevent accumulation of polymer on the surfaces of the collar 1050, the temperature of collar 1050
25 is held at a selected temperature well above the polymer condensation temperature by a conventional temperature control system including a heat sink 2170 and cold sink 2175 thermally coupled to the collar 1050.

In accordance with another feature of the invention,
30 center and edge gas injection ports 2200, 2210 in the center and edge portions of the ceiling 1020, respectively, receive plasma precursor gases from independent gas supplies 2220, 2225. With this feature, the gas flow rates and gas mixtures at the wafer center and wafer periphery may be
35 adjusted independently to precisely compensate for wafer

center-to-edge processing non-uniformities. Thus, for example, the gas supply 2220 may furnish one plasma precursor gas mixture at one flow rate over the wafer center while the gas supply 2225 may furnish another plasma precursor gas mixture at another flow rate over the wafer periphery. While the drawing shows the gas supply 2220 coupled to a single gas inlet 2200 over the wafer center, multiple gas inlets overlying the wafer center or a showerhead configuration may be employed to control the gas flow over the wafer center. While the drawing shows the gas supply 2225 coupled to multiple gas inlets 2210 extending radially through the side wall or skirt 1010 toward the wafer edge, the gas supply 2225 may be coupled instead to gas inlets extending toward the wafer edge either downwardly through the ceiling 1020 or upwardly through the collar 1050 to control gas flow over the wafer edge.

Plasma source RF power is applied to the coil inductor 1040 across the coil terminals 2310, 2320. Bias RF power is applied to the wafer pedestal 1060 through the pedestal terminal 2330. RF power or a ground potential is applied to the semiconductor enclosure electrode 1030 (including the disk ceiling 1020 and cylindrical skirt 1010) through the terminal 2340. Various ways are disclosed above in this specification for providing separate RF power supplies to the semiconductor window enclosure 1030, the induction coil 1040 and wafer pedestal 1060 (as shown, for example, in FIG. 1, 5, 19 or 23), or splitting RF power thereto from common RF power supplies (as shown, for example, in FIG. 4, 18, 19 or 20), any one of which may be applied to the embodiment of FIG. 48A. Moreover, various induction coil geometries are disclosed above in this specification (as shown, for example, in FIG. 30A, 30B, 30C, 31A, 31B, 31C, 32, 33 or 34), any one of which may be employed in carrying out the embodiment of FIG. 48A.

Thus, the embodiment of FIG. 48A has three independent electrodes, namely (a) the wafer pedestal 160, (b) the semiconductor ceiling 1020 and (c) the semiconductor skirt 1010. Each one of these three "electrodes" can be larger or smaller in effective area than the other two, depending upon the desired interaction between the particular "electrode" and the plasma. By such an increase or decrease in effective area of one the three "electrodes" relative to the other two, plasma ion flux and energy at the one electrode may be apportioned relative to the other electrodes. Specifically, a decrease in an electrode's effective area relative to the other electrodes increases the plasma ion flux and energy at the one electrode. This provides another way to control the interaction between the one electrode and the plasma and can be used, for example, to alleviate RF bias power requirements or temperature requirements in achieving a desired electrode-plasma interaction. As one example of a desired electrode-plasma interaction, in one mode of the present invention it is preferable to prevent deposition of materials onto the semiconductor enclosure interior surfaces, including the two semiconductor electrodes (i.e., the skirt 1010 and the ceiling 1020). By thus maintaining the semiconductor electrode free of deposited contaminants (e.g., polymer precursors), wafer contamination due to flaking off of deposited materials from the electrode is prevented while at the same time the electrode is left uncovered to enable it to continue participating favorably in the plasma process chemistry. For example, the electrode may be a silicon-containing material and the plasma process may be a silicon oxide etch process employing a fluorine-containing process gas, in which case the electrode provides sputtered silicon material into the plasma to scavenge fluorine. In any case, alleviation RF bias power requirements or electrode temperature requirements may be accomplished by adjusting

any one, or some, or all of the following three parameters at the one "electrode": (a) RF bias power applied to the one electrode, (b) temperature of the one electrode, and (c) effective area of the one electrode relative to the other electrodes' effective areas. Thus, if it is desired to minimize the temperature of one of the electrodes and to minimize the RF bias power applied to the one electrode while nevertheless preventing deposition of materials (such as polymer precursors) on the one electrode, then the electrode's effective area may be decreased to increase the plasma ion flux and energy at the one electrode so as to compensate for a reduced electrode temperature and electrode RF bias power. In this manner, the selection of effective electrode area can alleviate RF bias power and temperature requirements in attaining a desired interaction between the electrode and the plasma.

In the embodiment of FIG. 48A, the coil inductor 1040 may be divided into electrically separate inner and outer coil inductors. For example, such inner and outer coil inductors are illustrated in FIG. 52 as inner and outer coil inductors 2410 and 2420. Various ways of separately driving such inner and outer coil inductors in combination with a semiconductor window enclosure are disclosed above in this specification (as shown, for example, in FIG. 6, 16), any one of which may be employed in carrying out the embodiment of FIG. 48A. In a special case in which the wafer-to-ceiling distance is small, one advantage of separately controlling the outer antenna coil 2420 is that the plasma density over the wafer center, which is lower than that at the wafer periphery due to the small wafer-to-ceiling distance, may be enhanced relative to that at the wafer periphery by decreasing the RF plasma source power applied to the outer coil inductor 2420 relative to that applied to the inner coil inductor 2410.

While the embodiment of FIG. 48A exhausts the processing region 1035 laterally to the pumping annulus 1070, the embodiment of FIG. 48B exhausts downwardly parallel to the axis of the cylindrical skirt 1010 to the pump 1080. Optional magnet rings 2130a, 2135a block downward leakage of plasma from the processing region 1035 to the pumping annulus. In the embodiment of FIG. 48A, in order to further block plasma leakage the aperture 1075 has a relatively high aspect ratio, so that leaking plasma ions or electrons tend to collide and be absorbed on the interior surfaces of the aperture 1075 before completing their passage therethrough. Another feature that reduces plasma leakage is the meandering path through the opening 1051 between the collar 1050 and the bottom of the skirt 1010. As shown in the drawing, the collar 1050 and the bottom of the skirt 1010 have conforming overlapping step shapes --in the manner of overlapping baffles-- which constrain any plasma passing therebetween to follow a meandering path through the gap 1051, thereby increasing the incidence of plasma collision with the surfaces thereof.

In FIG. 48A, the cylindrical skirt 1010 is electrically separated from the disk ceiling 1020 that each may be connected to independent RF power sources through terminals 2340 and 2340a respectively. This permits the plasma conditions near the wafer periphery to be controlled by the separate RF potential applied to the terminal 2340a on the cylindrical skirt 1010 independently of the RF potential applied to the terminal 2340 of the disk ceiling 1020 which tends to affect plasma conditions near the wafer center. Various ways of controlling the RF potential on two electrical separate sections of the semiconductor window enclosure are disclosed above in this specification (as shown, for example, in FIG. 42, 46, 10, 11 or 12), any one of which may be employed in carrying out the embodiment of FIG. 48A.

Since the skirt 1010, the ceiling 1020 and the wafer pedestal 1060 are susceptible of being used as independent electrodes, any one of them may be electrically grounded relative to the others, while the ungrounded ones may be driven with the same or different power sources. For example, as illustrated in FIG. 48C, a first RF power source 3010 of frequency f_1 is coupled to the semiconductor ceiling electrode 1020, while filters 3020 and 3030 prevent coupling of RF power at frequencies f_2 and f_3 back to an RF impedance match circuit 3035. A second RF power source 3040 of frequency f_2 is coupled to the semiconductor ceiling skirt 1010, while filters 3050 and 3060 prevent coupling of RF power at frequencies f_1 and f_3 back to an RF impedance match circuit 3065. A third RF power source 3070 of frequency f_3 is coupled to the wafer pedestal 1060, while filters 3080 and 3090 prevent coupling of RF power at frequencies f_1 and f_2 back to an impedance match circuit 3095. The embodiment of FIG. 48C may be modified as desired by grounding any one of the three elements 1020, 1010 or 1060.

Forming the semiconductor enclosure 1030 as two separate silicon pieces 1010, 1020 provides an additional advantage of ease of fabrication, and is therefore preferable.

FIG. 49 illustrates an embodiment corresponding to that of FIG. 48A except that the skirt 1010 and ceiling 1020 are not electrically insulated from one another and may even be formed as a single integral monolithic silicon piece.

FIG. 50 illustrates how the disk-shaped semiconductor ceiling 1020 may be divided into an inner center disk portion 1020a and a peripheral annular portion 1020b from which the cylindrical skirt 1010 extends downwardly. As in the embodiment of FIG. 49, the plasma conditions at the wafer center and wafer edge may be controlled independently by separate RF bias signals applied to the separate terminals 2340 and 2340a, respectively. Any one of the

various ways disclosed above for controlling separate sections of the semiconductor window enclosure 1030 referred to above with reference to the embodiment of FIG. 48A may be employed in carrying out the embodiment of FIG. 50.

5 FIG. 51 illustrates how the semiconductor window enclosure 1030 may be divided into three electrically separate portions, including (1) an inner disk portion 1020a of the ceiling 1020, (2) an outer annular portion 1020b of the ceiling 1020 and (3) the skirt 1010 separated from the
10 annular portion 1020b. Three separate RF signals may be applied to the three portions through the terminal 2340 to the inner disk portion 1020a, through the terminal 2340a to the skirt 1010 and through the terminal 2340b to the outer annular portion 1020b.

15 FIG. 52 illustrates how the embodiment of FIG. 50 can be combined with independent inner and outer induction coils 2410, 2420 for independent control of plasma conditions at over the wafer center and the wafer edge. Terminals 2430, 2435 and 2440, 2445 to the inner and outer induction coils
20 2410, 2420, respectively may be driven by separate RF power supplies or by splitting RF power from a common supply. Various ways of powering such inner and outer induction coils 2410, 2420 in combination with separately driven portions of the semiconductor window enclosure 1030 are
25 disclosed above in this specification (as shown, for example, in FIG. 42, 43 or 46), any one of which may be employed in carrying out the embodiment of FIG. 52.

 FIG. 53 illustrates how the embodiment of FIG. 51 may be combined with the separate inner and outer coil inductors
30 2410, 2420.

 FIG. 54 illustrates how the embodiment of FIG. 48A may be combined with a cylindrical side coil 2610 wound around the semiconductor skirt 1010, in a manner analogous to that of the embodiment of FIG. 10. Plasma RF source power is
35 applied to the side coil 2610 through terminals 2620, 2630.

Preferably, the top coil 1040 and the side coil 2610 are separated by a distance equal to at least about twice the skin depth of the RF field in the plasma.

5 Optionally, the coil inductor 1040 overlying the ceiling 1020 may be eliminated in favor of the side coil 2610, in analogy with the embodiments of FIGS. 7, 8 and 9. In such a case only the skirt 1010 is required to be a semiconductor material providing a cylindrical semiconductor window enclosure 1030, while the ceiling 1020 may be an
10 insulator (such as silicon nitride, for example). Any one of the techniques of FIGS. 7, 8 or 9 for separately applying RF power to the cylindrical semiconductor window enclosure, the side coil and the wafer pedestal may be employed in carrying out the embodiment of FIG. 54.

15 FIG. 55 illustrates how the embodiment of FIG. 48A whose semiconductor window enclosure 1030 is divided into a ceiling 1020 and a skirt 1010, may be combined with the cylindrical side coil 2610 wound around the skirt 1010. Any one of the ways illustrated in FIGS. 10, 11 and 12 of
20 applying RF power to the separate ceiling sections and top and side coil inductors may be employed in carrying out the embodiment of FIG. 55.

 FIG. 56 illustrates how the embodiment of FIG. 50, whose semiconductor window enclosure 1030 is divided into an
25 inner disk portion 1020a and an outer annulus portion 1020b with the skirt 1010 may be combined with the side coil 2610 wound around the skirt 1010. Any one of the ways illustrated in FIGS. 10, 11 and 12 of applying RF power to the separate ceiling sections and top and side coil
30 inductors may be employed in carrying out the embodiment of FIG. 56.

 FIG. 57 illustrates how the embodiment of FIG. 51, whose semiconductor window enclosure 1030 is divided into an inner disk portion 1020a, an outer annulus portion 1020b and

the skirt 1010, may be combined with the side coil 2610 wound around the skirt 1010.

FIG. 58 illustrates how the ceiling 1020 of the embodiment of FIG. 48A may be modified to have a dome shape. Preferably, the dome shape is a multi-radius dome shape in which the radius of the dome increases from edge to center. Preferably, but not necessarily, the ceiling coil inductor 1040 is congruent with the dome shape of the ceiling 1020. Similarly, FIG. 59 illustrates how the ceiling 1020 of the embodiment of FIG. 49 may be modified to have a dome shape. Likewise, FIG. 60 illustrates how the ceiling 1020 of the embodiment of FIG. 50 may be modified to have a dome shape, FIG. 61 illustrates how the ceiling 1020 of the embodiment of FIG. 51 may be modified to have a dome shape, FIG. 62 illustrates how the ceiling 1020 of the embodiment of FIG. 52 may be modified to have a dome shape, FIG. 63 illustrates how the ceiling 1020 of the embodiment of FIG. 53 may be modified to have a dome shape, FIG. 64 illustrates how the ceiling 1020 of the embodiment of FIG. 54 may be modified to have a dome shape, FIG. 65 illustrates how the ceiling 1020 of the embodiment of FIG. 55 may be modified to have a dome shape, FIG. 66 illustrates how the ceiling 1020 of the embodiment of FIG. 56 may be modified to have a dome shape, and FIG. 67 illustrates how the ceiling 1020 of the embodiment of FIG. 57 may be modified to have a dome shape.

FIG. 68A illustrates a cross-sectional view of a first embodiment of the magnetic confinement feature referred to previously in connection with the opposing magnet rings 2130, 2135 of FIG. 48A. In FIG. 68A, the magnet rings have poles which are oriented end-to-end with opposing poles facing one another. In FIG. 68B, the opposing magnet poles are oriented side-to-side in opposing directions so that opposite pair of poles are in juxtaposed alignment. In FIG. 68C, the opposing magnet poles are oriented along diagonal acute angles relative to the direction of displacement

between the two magnet rings 2030, 2035. FIGS. 68D and 68E correspond to FIGS. 68B and 68C, respectively, except that like magnetic poles are juxtaposed rather than opposing magnetic poles. Other arrangements which provide the requisite diversion of ions from a straight path through the slit valve 1075 or other large opening may be provided in carrying out the invention.

While the embodiments of FIGS. 48A-68C have been described with reference to a ceiling and skirt of different shapes (i.e., either disk and cylinder or disk and dome, respectively), they may be of the same shape or different shapes formed by rotation of curves, including hemispherical, multi-radius dome, cylindrical, conical, truncated conical or the like.

While the foregoing description has made reference to a rotationally symmetric inductive antenna, such an antenna is not required in carrying out the invention, and the antenna may be of any other form capable of inductively coupling RF power into the chamber. Thus, the inductive antenna, as this term is employed in this specification and in the claims appended hereto, is any current-carrying element adjacent the plasma that at least inductively couples RF power to the plasma, and therefore need not be a coil and moreover need not be located adjacent the reactor chamber ceiling, but could be adjacent any other suitable location, such as the chamber side wall. In fact, an inductive antenna can be dispensed with entirely, as in the embodiment of FIG. 69. FIG. 69 corresponds to the embodiment of FIG. 48A in which the inductive antenna 1040 has been eliminated. Instead, RF power is capacitively coupled to the plasma from, for example, the pair of electrodes comprising the semiconductor ceiling 1020 and the wafer pedestal 1060.

While the description has made reference to plasma confinement magnets which are permanent magnets, electro-magnets may be employed as the plasma confinement magnets.

While the embodiments of FIGS. 48A-68C have been described with reference to a plasma etch reactor, the invention may also be employed in a plasma deposition reactor, such as a chemical vapor deposition (CVD) plasma reactor. In this case, the process may be carried out in such a manner that deposition occurs not only on the wafer but also on the chamber walls. Alternatively, the walls may be biased with sufficient RF power so that no deposition accumulates on the chamber interior walls even while material is being deposited on the wafer. This provides a great advantage particularly with, for example, a silicon oxide CVD plasma reactor. This is because, without the present invention, the interior walls of such a reactor must be periodically cleaned. Such a cleaning operation is difficult because silicon dioxide etches very slowly, even in a fluorine-containing cleaning gas, unless the surface temperature is well-above the chemical etch threshold temperature.

Alternatively, the invention can function as a post-processing self-cleaning CVD reactor chamber by introducing a cleaning gas (e.g., a fluorine-containing gas) into the chamber, applying RF power to each semiconductor enclosure element and suitably adjusting the temperature thereof. In such an alternative embodiment, during CVD processing of a production wafer the reactor could be operated in the manner of a conventional CVD reactor without utilizing any features of the present invention. Thereafter, a cleaning operation is performed employing all the features of the present invention. During such a cleaning operation, the rate at which deposited contaminants of the interior surfaces of the semiconductor enclosure are etched away is enhanced, without necessarily having to raise the surface temperature, by applying RF bias power to the semiconductor enclosure, in accordance with the present invention.

The shape of the semiconductor enclosure may be varied by the skilled worker to meet unique requirements of a particular application. For example, in the embodiments of FIGS. 48A and 48B, the silicon skirt 1010 has an L-shaped cross-section (formed by the semiconductor cylindrical portion of the skirt 1010 and the semiconductor annular foot 1011) to increase the radial distance from the wafer periphery to the vertical surface of the skirt 1010, while in the embodiments of the other drawings the interior surface of the skirt 1010 is completely straight and is therefore closer to the wafer periphery. Such variations in the shape of the semiconductor skirt 1010 may be carried out in any one of the illustrated embodiments.

Varying the Window Electrode Temperature and RF Bias Power:

Use of the three RF-biased and temperature-controlled electrodes, such as the wafer pedestal 1060, the ceiling 1020 and the skirt 1010 of FIG. 48A, two of which (the ceiling 1020 and the skirt 1010) comprise a semiconductor material such as silicon and therefore furnish free silicon to the plasma chemistry, enhances various processing characteristics including etch rate and etch selectivity. The strong dissociation characteristics of the plasma promote entry of the free silicon into the gas phase to combine with and/or scavenge free fluorine.

One problem with a plasma etch reactor is that such dissociation characteristics of the plasma cause high concentrations of free fluorine when fluorine-containing gas chemistry is used, for example, to etch oxide. This increases the etch rate of oxide but also increases the etch rate of associated wafer materials which are not to be etched, such as polysilicon and, thus, reduces the oxide-to-polysilicon etch selectivity.

Solution to the problem of reduced oxide-to-polysilicon etch selectivity is facilitated in the present invention by

the silicon-containing electrodes 1010, 1020 supplying free silicon to the plasma. The fluorine scavenging by the free silicon permits the use of a so-called "lighter" polymer chemistry (A "lighter" polymer chemistry is specified in the working examples given hereinbelow.) The advantage of a "lighter" polymer chemistry is that it has a lesser tendency to deposit polymer, including on the chamber surfaces and on the sidewalls of openings etched in a layer of the oxide on the wafer. By thus controlling polymer deposition on the sidewalls, etch profile is not distorted so that the openings etched in an oxide layer do not narrow with depth, thus enhancing etch profile and avoiding etch-stopping in deep oxide layers, which widens the process window. The result is increased oxide etch rate, increased oxide selectivity relative to polysilicon, and enhanced oxide etch anisotropy and vertical profile and decreased microloading.

Another advantage of the free silicon and lighter polymer chemistry is that the free silicon affects the polymerization reaction and results in a more stable passivating polymer deposition on the polysilicon than on the oxide so that the lighter polymer chemistry tends to form polymer more strongly on polysilicon or other non-oxide materials which are not to be etched and less rapidly on an oxide, such as silicon oxide, which is to be etched. This feature enhances the oxide-to-polysilicon etch selectivity.

In addition, the sacrificial silicon-containing electrodes operate synergistically with the use of carbon-containing and oxygen-containing gases such as carbon monoxide and/or carbon dioxide additives, to form polymers on polysilicon surfaces. The advantages of such carbon- and oxygen-containing additive gases are two-fold: (a) they provide a controlled inhibition of polymer buildup in etched openings through the oxide layer to prevent etch-stopping

and (b) they do not similarly inhibit polymer formation on polysilicon. This increases suppression of silicon etching to enhances oxide-to-polysilicon selectivity. As noted above, the lighter polymer chemistry avoids etch-stopping in etched openings through deep oxide layers by controlling the polymer formation on oxide surfaces. However, it does promote an appropriate amount of polymer formation on the oxide side walls to enhance etch anistotropy and thereby optimize vertical etch profile. In addition, the use of these features in a gas chemistry containing a CHF_3 main etchant is also synergistic in that the oxide etch rate increases along with a decrease in polysilicon etch rate relative to other fluorine chemistries, a significant advantage.

The foregoing features, in combination with controlling the temperature of the silicon-containing electrodes 1010, 1020, permits the exploitation of appropriate processing regimes to optimize etch selectivity. Several processing regimes are explored in the working examples given below.

Working Examples:

The foregoing concepts were explored in the following working examples using a plasma reactor corresponding in general to the embodiment of FIG. 48A in which the silicon ceiling electrode 1020 had a 10-inch diameter, the cylindrical skirt 1010 had a 10-inch diameter, the gap between the wafer 1065 and the ceiling 1020 was 4 inches, the skirt 1010 was grounded and a RF bias power was applied to the wafer pedestal 1060 and to the ceiling electrode 1020. Also, RF bias power of various selected power levels at 100 kHz was applied to the ceiling 1020. Plasma source RF power of 3250 Watts at 2.0 MHz was applied to the coil 1040 and RF bias power of 1400 Watts at 1.8 MHz was applied to the wafer pedestal 1060. The chamber 1035 was held at a pressure of 50 milliTorr. The light polymer chemistry was

provided by combined gas flows into the chamber 1035 of 800 sccm Argon, 100 sccm CHF_3 and 38 sccm CO_2 . The wafer was cooled using conventional techniques to avoid overheating. In each of the following examples, a 100-second etch time is employed.

In a first working example, the temperatures of the ceiling 1020 and skirt 1010 were both held at 150 degrees C and 500 Watts RF bias power was applied to the ceiling 1020. The result was an oxide-to-polysilicon etch selectivity of 15:1. This selectivity is inadequate for applications in which etched openings down 2 microns to the silicon substrate are 300% deeper than other etched openings down only 4000 Angstroms to an intermediate polysilicon layer. In fact, punch through the intermediate polysilicon layer was observed at both the wafer center and the wafer edge.

In a second working example, the RF bias power on the ceiling 1020 was increased to 1250 Watts, which increased the polysilicon-to-oxide etch selectivity somewhat to 20:1. However, the same punch through problem was observed in this working example as in the first working example.

In a third working example, the temperature on the ceiling 1020 and skirt 1010 was raised to 260 degrees C and no bias RF power was applied to the ceiling 1020. The oxide-to-polysilicon selectivity increased to 25:1 but the punch through problem persisted.

In a fourth working example, the 260 degree C electrode temperature was maintained while the bias RF power on the ceiling 1020 was increased to 250 Watts. In this case, the oxide-to-polysilicon selectivity jumped to 80:1 and the punch through problem was observed near the wafer edge only.

In a fifth example, the 260 degree C electrode temperature was maintained while the bias RF power on the ceiling electrode 1020 was doubled to 500 Watts. In this

case, the oxide-to-polysilicon selectivity increased to 120:1 and the punch through problem was eliminated.

In a sixth example, the 260 degree C electrode temperature was maintained while the bias RF power on the ceiling electrode 1020 was increased to 800 Watts. This increased the etch selectivity of oxide-to-polysilicon to 150:1. As in the previous example, there was no punch through of the intermediate polysilicon layer either at the wafer center or at the wafer edge.

While the invention has been described by specific reference to preferred embodiments, it is understood that variations and modifications thereof may be made without departing from the true spirit and scope of the invention.

What is claimed is:

1. A plasma reactor for processing a workpiece, said reactor comprising:

5 a reactor enclosure defining a processing chamber;
a base within said chamber for supporting said workpiece during processing thereof;
a semiconductor window electrode overlying said base;

10 a gas inlet system for admitting a plasma precursor gas into said chamber;

an electrical terminal coupled to said semiconductor window electrode;

15 an inductive antenna adjacent one side of said semiconductor window electrode opposite said base for coupling power into the interior of said chamber through said semiconductor window electrode.

2. The plasma reactor of Claim 1 wherein said workpiece is a planar substrate, said semiconductor window electrode comprises a ceiling portion of said reactor enclosure generally parallel to and overlying said planar substrate, and said inductive antenna overlies said ceiling portion and faces said planar substrate through said semiconductor window electrode.

25 3. The plasma reactor of Claim 1 wherein said semiconductor workpiece is a planar substrate, said semiconductor window electrode comprises a sidewall portion of said reactor enclosure generally perpendicular to and surrounding a periphery of said substrate and said inductive antenna is adjacent said sidewall portion.

30 4. The plasma reactor of Claim 2 wherein said inductive antenna overlying said ceiling portion comprises an arcuately extending elongate conductor disposed generally parallel to the plane of said planar substrate.

35 5. The plasma reactor of Claim 4 wherein said inductive antenna is planar.

6. The plasma reactor of Claim 4 wherein said inductive antenna is dome-shaped.

7. The plasma reactor of Claim 3 wherein said inductive antenna adjacent said sidewall portion comprises a conductive coil wound around said sidewall portion.

8. The plasma reactor of Claim 2 further comprising a bias RF power source coupled to said substrate, said electrical terminal of said semiconductor window electrode being connected so as to enable said semiconductor window electrode to be a counter electrode to the bias RF power source coupled to said substrate.

9. The plasma reactor of Claim 8 wherein said electrical terminal of said semiconductor window electrode is connected to ground to provide a ground plane parallel to and over said planar substrate.

10. The plasma reactor of Claim 1 wherein said electrical terminal of said semiconductor window electrode is grounded so that said semiconductor window electrode provides a uniform ground plane relative to said workpiece.

20

11. The plasma reactor of Claim 1 further comprising:
a plasma source RF power generator coupled to said inductive antenna for supplying power for said inductive field;

25

a plasma bias RF power generator coupled to said workpiece, wherein said electrical terminal of said semiconductor window electrode is connected to a counter potential of said bias RF power generator.

12. The plasma reactor of Claim 11 wherein said counter potential of said bias RF power generator is ground.

30

13. The reactor of Claim 2 further comprising a power splitter having one output coupled to said semiconductor window electrode and another output coupled to said

substrate and an input for receiving power from a common source.

14. The reactor of Claim 13 wherein said ceiling portion is one of:

- 5 (a) planar, and
- (b) dome-shaped.

15. The reactor of Claim 2 further comprising a first power source coupled to said semiconductor window electrode and a second power source coupled to said planar substrate.

10

16. The reactor of Claim 15 wherein said ceiling portion is one of:

- (a) planar, and
- (b) dome-shaped.

15

17. The reactor of Claim 2 wherein said inductive antenna comprises an inner antenna portion overlying a center of said planar substrate and an outer antenna portion overlying a periphery of said planar substrate and electrically separated from said inner antenna portion, said reactor further comprising:

20

a first power source node coupled to said inner antenna portion; and

a second power source node coupled to said outer antenna portion.

25

18. The reactor of Claim 17 wherein said ceiling portion is one of:

- (a) planar, and
- (b) dome-shaped.

19. The reactor of Claim 2 further comprising a power splitter having one output coupled to said semiconductor window electrode and another output coupled to said inductive antenna and an input for receiving power from a common source.

30

20. The reactor of Claim 19 wherein said ceiling portion is one of:

35

- (a) planar, and
- (b) dome-shaped.

21. The reactor of Claim 2 further comprising a power splitter having one output coupled to said planar substrate and another output coupled to said inductive antenna and an input for receiving power from a common source.

22. The reactor of Claim 21 wherein said electrical terminal of said semiconductor window electrode is connected to RF ground.

23. The reactor of Claim 21 wherein said ceiling portion is one of:

- (a) planar, and
- (b) dome-shaped.

24. The plasma reactor of Claim 3 further comprising a bias RF power source coupled to said planar substrate, said electrical terminal of said semiconductor electrode being connected so as to enable said semiconductor window electrode to be a counter electrode to the bias RF power source coupled to said planar substrate.

25. The plasma reactor of Claim 24 wherein said electrical terminal of said semiconductor window electrode is connected to ground to provide a ground plane for said planar substrate.

26. The reactor of Claim 3 further comprising a power splitter having one output coupled to said semiconductor window electrode and another output coupled to said planar substrate and an input for receiving power from a common source.

27. The reactor of Claim 26 further comprising a plasma source RF power generator coupled to said inductive antenna.

28. The reactor of Claim 3 further comprising a power splitter having one output coupled to said semiconductor window electrode and another output coupled to said

inductive antenna and an input for receiving power from a common source.

29. The reactor of Claim 28 further comprising a bias RF power generator coupled to said planar substrate.

5 30. The reactor of Claim 3 further comprising a power splitter having one output coupled to said planar substrate and another output coupled to said inductive antenna and an input for receiving power from a common source.

10 31. The reactor of Claim 30 wherein said electrical terminal of said semiconductor window electrode is connected to RF ground.

32. The reactor of Claim 30 further comprising an independent RF power generator coupled to said electrical terminal of said semiconductor window.

15 33. The reactor of Claim 2 further comprising:
a side semiconductor window electrode plate comprising a sidewall portion of said reactor enclosure generally perpendicular to and surrounding a periphery of said substrate; and

20 a side inductive antenna element adjacent said sidewall portion.

34. The plasma reactor of Claim 33 further comprising a bias RF power source coupled to said substrate, said electrical terminal of said semiconductor window electrode
25 being connected so as to enable said semiconductor window electrode to be a counter electrode to the bias RF power source coupled to said substrate.

35. The plasma reactor of Claim 34 wherein said electrical terminal of said semiconductor window electrode
30 is connected to ground to provide a ground plane parallel to and over said planar substrate.

36. The reactor of Claim 34 wherein said ceiling portion is one of:

- 35 (a) planar, and
(b) dome-shaped.

37. The reactor of Claim 33 further comprising a power splitter having one output coupled to said semiconductor window electrode and another output coupled to said substrate and an input for receiving power from a common source.

38. The reactor of Claim 37 wherein said ceiling portion is one of:

- (a) planar, and
- (b) dome-shaped.

39. The reactor of Claim 33 further comprising a first power source coupled to said semiconductor window electrode and a second power source coupled to said planar substrate.

40. The reactor of Claim 39 wherein said ceiling portion is one of:

- (a) planar, and
- (b) dome-shaped.

41. The reactor of Claim 17 further comprising a power splitter having one output coupled to said first power source node of said inner inductive antenna portion and another output coupled to said second power source node of said outer inductive antenna portion, and an input for receiving power from a common source.

42. The reactor of Claim 41 wherein said ceiling portion is one of:

- (a) planar, and
- (b) dome-shaped.

43. The reactor of Claim 33 further comprising a power splitter having one output coupled to said inductive antenna overlying said ceiling portion and another output coupled to said inductive antenna element adjacent said sidewall portion, and an input for receiving power from a common source.

44. The reactor of Claim 43 wherein said ceiling portion is one of:

- (a) planar, and
- (b) dome-shaped.

45. The reactor of Claim 1 wherein:

5 said semiconductor window and said workpiece are
separately driven with RF power;

 said workpiece is a counter electrode for said
semiconductor window electrode; and

 said semiconductor window electrode is a counter
electrode for said workpiece.

10 46. The reactor of Claim 45 further comprising:

 a first RF power source of a first frequency
coupled to said semiconductor window electrode;

 a second RF power source of a second frequency
coupled to said workpiece;

15 a first ground pass filter connected between RF
ground and said semiconductor window electrode, said first
ground pass filter blocking RF power around said first
frequency and passing RF power around said second frequency;
and

20 a second ground pass filter coupled between RF
ground and said workpiece, said second filter blocking RF
power around said second frequency and passing RF power
around said first frequency.

 47. The reactor of Claim 46 further comprising:

25 a first isolation filter connected between said
first RF power source and said semiconductor window
electrode for blocking RF power near said second frequency;
and

30 a second isolation filter connected between said
second RF power source and said workpiece for block RF power
near said first frequency.

 48. The reactor of Claim 46 wherein said semiconductor
window electrode comprises a ceiling portion of said
enclosure facing said workpiece and is one of:

35 (a) planar, and

(b) dome-shaped.

49. The reactor of Claim 1 further comprising a conductive backplane lying on an external surface of said semiconductor window electrode, said conductive backplane
5 being connected directly to said electrical terminal, said conductive electrode comprising plural apertures therein for admitting an induction field of said inductive antenna through said conductive backplane.

50. The reactor of Claim 49 wherein said conductive
10 backplane comprises plural conductive radial arms separated by said apertures.

51. The reactor of Claim 49 wherein said apertures have a characteristic width on the order of approximately a thickness of said semiconductor window electrode.

15 52. The reactor of Claim 1 further comprising a structurally supportive substrate bonded to an exterior surface of said semiconductor window electrode.

53. The reactor of Claim 52 further comprising a conductive backplane between said window electrode and said
20 supportive substrate, said conductive backplane being connected directly to said electrical terminal, said conductive backplane comprising plural apertures therein for admitting an induction field of said inductive antenna through said conductive backplane.

25 54. The reactor of Claim 52 wherein said structurally supportive substrate comprises an antenna holder supporting said inductive antenna.

55. The reactor of Claim 54 further comprising a conductive backplane between said window electrode and said
30 antenna holder, said conductive backplane being connected directly to said electrical terminal, said conductive electrode comprising plural apertures therein for admitting an induction field of said inductive antenna through said conductive backplane.

56. The reactor of Claim 55 wherein said antenna holder comprises an insulating material.

57. The reactor of Claim 54 wherein said antenna holder comprises a conductive material, said reactor further comprising an insulating layer between said inductive antenna and said conductive antenna holder.

58. The reactor of Claim 57 wherein said conductive antenna holder functions as a conductive backplane on an exterior surface of said semiconductor window electrode.

59. The reactor of Claim 57 wherein:
said inductive antenna comprises an elongate conductor extended in an arcuate path; and
said conductive antenna holder comprises a
elongate groove extending in said arcuate path and holding
said elongate conductor, said groove being open at a surface
of said conductive antenna holder facing said semiconductor window electrode.

60. The reactor of Claim 57 wherein:
said conductive antenna holder comprises an recess
in a surface of said conductive antenna holder facing said semiconductor window electrode; and
said inductive antenna comprises plural elongate conductive turns held within said recess.

61. The reactor of Claim 57 wherein:
said conductive antenna holder comprises an inner annular recess and an outer annular recess concentric with said inner recess in a surface of said conductive antenna holder facing said semiconductor window electrode; and
said inductive antenna comprises inner and outer sets annular concentric conductive windings held within respective ones of said inner and outer annular recesses.

62. The reactor of Claim 57 further comprising a conductive backplane between said window electrode and said antenna holder, said conductive backplane being connected directly to said electrical terminal, said conductive

electrode comprising plural apertures therein for admitting an induction field of said inductive antenna through said conductive backplane.

5 63. The reactor of Claim 1 wherein said inductive antenna comprises a non-concentrically arcuately extending elongate conductor.

64. The reactor of Claim 63 wherein said non-concentrically arcuately extending elongate conductor comprises a center conductive element and plural spirals radiating outwardly from said center conductive element.
10

65. The reactor of Claim 63 wherein said non-concentrically arcuately extending elongate conductor comprises a circumferential conductive element and plural spirals radiating inwardly from said circumferential conductive element.
15

66. The reactor of Claim 63 wherein said non-concentrically arcuately extending elongate conductor comprises:

20 a center conductive element and plural spirals radiating outwardly from said center conductive element; and
a circumferential conductive element and plural spirals radiating inwardly from said circumferential conductive element.

67. The reactor of Claim 63 wherein said semiconductor window electrode comprises a ceiling portion of said enclosure facing said workpiece and is one of:
25

- (a) planar, and
- (b) dome-shaped.

68. The reactor of Claim 1 wherein said inductive antenna comprises an elongate conductor extending in a non-planar path.
30

69. The reactor of Claim 68 wherein said non-planar path comprises a three-dimensional helix.

70. The reactor of Claim 68 wherein said non-planar path comprises dual concentric three-dimensional helical paths.

5 71. The reactor of Claim 68 wherein said non-planar path comprises:

first dual concentric three-dimensional helical paths constituting an inner portion; and

10 second dual concentric three-dimensional helical paths constituting an outer portion concentric with said inner portion.

72. The reactor of Claim 68 wherein said non-planar path comprises stacked spiral paths.

15 73. The reactor of Claim 2 wherein said gas inlet system comprises a set of gas inlet ports through said semiconductor window electrode over said planar substrate.

74. The reactor of Claim 73 further comprising:
a center gas feed top sealed onto an exterior surface of said semiconductor window electrode; and
20 a gas manifold formed between said center gas feed top and said semiconductor window electrode, said gas manifold encompassing said gas inlet ports.

25 75. The reactor of Claim 74 further comprising:
a semiconductor baffle extending across said manifold and dividing said manifold into a pair of sub-manifolds, one of said sub-manifolds being adjacent said center gas feed top and the other of said sub-manifolds being adjacent said gas inlet ports; and
plural gas feed passages through said semiconductor baffle offset from said gas inlet ports.

30 76. The reactor of Claim 1 further comprising a grounded Faraday shield layer between and insulated from said inductive antenna and said semiconductor window electrode.

77. The reactor of Claim 76 wherein said semiconductor window electrode, said inductive antenna and said Faraday shield layer are all one of:

(a) dome-shaped;

(b) cylindrical.

78. The reactor of Claim 1 wherein said semiconductor window electrode comprises silicon.

79. The reactor of Claim 2 wherein said semiconductor electrode is within 1-20 centimeters of said planar substrate and is parallel therewith.

80. The reactor of Claim 1 wherein:
said inductive antenna is outside said chamber;
and

said semiconductor window electrode comprises a ceiling portion of said reactor enclosure.

81. The reactor of Claim 1 wherein:
said reactor enclosure comprises a ceiling portion overlying said base;

said semiconductor window electrode is inside said chamber under said ceiling portion; and

said inductive antenna is inside said chamber on a side of said semiconductor window electrode opposite said base.

82. The reactor of Claim 1 further comprising at least one of:

(a) a heat sink thermally coupled to said semiconductor window for controlling a temperature of said semiconductor window;

(b) a cold sink thermally coupled to said semiconductor window for controlling a temperature of said semiconductor window.

83. The reactor of Claim 1 wherein said semiconductor window is comprised of a material containing silicon.

84. The reactor of Claim 1 wherein said semiconductor window is a scavenger for fluorine.

85. The reactor of Claim 73 wherein said gas inlet ports are generally confined to a center portion of said semiconductor window electrode.

5 86. The reactor of Claim 73 wherein said gas inlet ports are located near a peripheral portion of said semiconductor window electrode.

87. The reactor of Claim 1 wherein said semiconductor window electrode is segmented into sub-portions.

10 88. The reactor of Claim 87 wherein said subportions are concentric.

89. The reactor of Claim 87 wherein said subportions comprise:

15 a semiconductor window center disk; and
a semiconductor window peripheral annulus
concentric with said center disk.

20 90. The reactor of Claim 89 further comprising an RF power splitter connected to receive RF power from a single source and having a pair of RF power outputs connected, respective ones of said pair of RF power outputs being connected to said semiconductor window center disk and semiconductor window peripheral annulus.

25 91. The reactor of Claim 89 wherein said semiconductor window disk and semiconductor window annulus are conformal with a dome shape.

30 92. The reactor of Claim 17 wherein said semiconductor window electrode is segmented into concentric sub-portions comprising:

a semiconductor window center disk, and
a semiconductor window peripheral annulus
concentric with said center disk.

35 93. The reactor of Claim 41 wherein said semiconductor window electrode is segmented into concentric sub-portions comprising a semiconductor window center disk and a semiconductor window peripheral annulus concentric with said center disk, said reactor further comprising:

a second RF power splitter connected to receive RF power from a single source and having a pair of RF power outputs connected, respective ones of said pair of RF power outputs being connected to said semiconductor window center disk and semiconductor window peripheral annulus.

94. The reactor of Claim 93 wherein said semiconductor window and said inductive antenna are one of:

- (a) planar; and
- (b) dome-shaped.

95. The reactor of Claim 93 wherein said semiconductor window center disk is planar and said semiconductor window peripheral annulus comprises a cylindrical side wall.

96. The reactor of Claim 89 further comprising an RF power splitter having a pair of RF power outputs connected, respectively, to said semiconductor window center disk and said base whereby to split RF power from a single source between said disk and said base.

97. The reactor of Claim 96 wherein said semiconductor window peripheral annulus provides an RF return path.

98. The reactor of Claim 97 wherein said semiconductor window is grounded.

99. The reactor of Claim 96 wherein said semiconductor window and said inductive antenna are one of:

- (a) planar; and
- (b) dome-shaped.

100. A plasma reactor for processing a workpiece, said reactor comprising:

- a reactor enclosure defining a chamber;
- a base within said chamber for supporting said workpiece;
- a semiconductor window overlying said base; and
- an inductive antenna adjacent a side of said semiconductor window opposite said base.

101. The plasma reactor of Claim 100 wherein said semiconductor window is electrically floating.

102. The plasma reactor of Claim 100 wherein said semiconductor window is an electrode and is connected to an electrical potential source, said electrical potential source comprising one of:

- 5 (a) an RF power source, and
 (b) RF ground.

103. The reactor of Claim 100 further comprising at least one of:

- 10 (a) a heat sink thermally coupled to said semiconductor window for controlling a temperature of said semiconductor window;

 (b) a cold sink thermally coupled to said semiconductor window for controlling a temperature of said semiconductor window.

15 104. The reactor of Claim 100 wherein said semiconductor window is comprised of a material containing silicon.

105. The reactor of Claim 100 wherein said semiconductor window is a scavenger for fluorine.

20 106. The reactor of Claim 100 wherein said semiconductor window and said inductive antenna are both inside said chamber.

107. The reactor of Claim 100 wherein said inductive antenna is outside of said chamber.

25 108. The reactor of Claim 107 wherein said semiconductor window forms a portion of said reactor enclosure.

109. A plasma reactor for processing a planar substrate, said reactor comprising:

- 30 a reactor enclosure defining a processing chamber;
 a base within said chamber for supporting said planar substrate during processing thereof;
 a semiconductor window overlying said base;
 a gas inlet system comprising a set of gas inlet
35 ports through said semiconductor window electrode over said

planar substrate for admitting a plasma precursor gas into the portion of said chamber overlying said planar substrate;

an inductive antenna overlying said semiconductor window for coupling power into the interior of said chamber through said semiconductor window, said inductive antenna comprising:

(a) an inner antenna portion overlying a center of said planar substrate, and

(b) an outer antenna portion overlying a periphery of said planar substrate and electrically separated from said inner antenna portion so as to be separately controllable.

110. The reactor of Claim 109 further comprising:

a power splitter having one output coupled to said inner antenna portion and another output coupled to said outer antenna portion, and an input for receiving power from a common source; and

a controller regulating said power splitter to apportion of RF power between said inner and outer antenna portions so as to optimize process uniformity across the surface of said planar substrate.

111. The reactor of Claim 109 wherein said ceiling portion is one of:

(a) planar, and

(b) dome-shaped.

112. A plasma reactor for processing a planar substrate, said reactor comprising:

a reactor enclosure defining a processing chamber;

a base within said chamber for supporting said planar substrate during processing thereof;

a semiconductor window overlying said base, said semiconductor window comprising:

(a) an inner window portion overlying a center of said planar substrate, and

(b) an outer window portion overlying a periphery of said planar substrate and electrically separated from said inner window portion so as to be separately controllable;

5 a gas inlet system comprising a set of gas inlet ports through said semiconductor window electrode over said planar substrate for admitting a plasma precursor gas into the portion of said chamber overlying said planar substrate;

10 an inductive antenna overlying said semiconductor window for coupling power into the interior of said chamber through said semiconductor window.

113. The reactor of Claim 112, wherein said inductive antenna comprises:

15 (a) an inner antenna portion overlying a center of said planar substrate, and

(b) an outer antenna portion overlying a periphery of said planar substrate and electrically separated from said inner antenna portion so as to be separately controllable.

20 114. The reactor of Claim 1 wherein said semiconductor window electrode comprises:

(a) an overlying top portion; and

25 (b) an encircling side portion, said top and side portions of said semiconductor window electrode enclosing a processing region of said chamber for confining plasma over said workpiece.

115. The reactor of Claim 114 wherein said encircling side portion extends from said top portion to said workpiece supporting base, said reactor further comprising:

30 a collar between said side portion and said base for constricting plasma flow between said side portion and said base by providing one of:

(a) a narrow passageway between said side portion and base,

(b) a meandering passageway between said side portion and base.

116. The reactor of Claim 114 further comprising:

a heater thermally coupled to said semiconductor window electrode; and

a cold plate thermally coupled to said semiconductor window electrode.

117. The reactor of Claim 114 further comprising:

a passageway through said semiconductor window electrode, said passageway comprising one of:

(a) a wafer slit valve aperture,

(b) a pumping annulus aperture,

(c) a gas inlet; and

plural plasma confinement magnets adjacent said passageway.

118. The reactor of Claim 117 wherein said passageway comprises a pumping annulus aperture, said reactor further comprising:

a pumping annulus proximal a periphery of said semiconductor window side portion;

a pump coupled to said pumping annulus; and

wherein said passageway extends through said semiconductor window side portion from said processing region to said pumping annulus.

119. The reactor of Claim 117 further comprising a protective encapsulation layer around each of said magnets.

120. The reactor of Claim 118 further comprising magnet cooler in thermal contact with at least one of said magnets.

121. The reactor of Claim 117 further comprising a removable liner covering an interior surface of said pumping annulus.

122. The reactor of Claim 121 further comprising a liner cooler in thermal contact with said removable liner.

123. The reactor of Claim 114 wherein said gas inlet system comprises at least one gas inlet through said semiconductor window electrode.

5 124. The reactor of Claim 123 wherein said plural gas inlets are independently controllable and overlies different radial locations of said workpiece for independently affecting plasma conditions over different radial locations of said workpiece.

10 125. The reactor of Claim 124 wherein said inductive antenna comprises electrically separate sub-antenna portions proximal different respective radial locations of said workpiece.

126. The reactor of Claim 125 wherein said separate sub-antenna portions comprise:
15 an inner antenna winding overlying said top portion of said semiconductor window electrode and overlying a center portion of said workpiece; and

an outer annular antenna portion overlying said top portion of said semiconductor window and overlying a peripheral annular portion of said workpiece.
20

127. The reactor of Claim 126 wherein said separate sub-antenna portions comprise:

a top antenna winding overlying said top portion of said semiconductor window electrode; and
25 a cylindrical side antenna winding wound around said side portion of said semiconductor window electrode.

128. The reactor of Claim 125 wherein said semiconductor window electrode comprises electrically separate sections comprising a center section and a side section and separate terminals for applying separate RF potentials to said separate sections of said semiconductor window electrode.
30

129. The reactor of Claim 128 wherein said separate semiconductor window electrode sections are proximal different respective radial locations of said workpiece.
35

130. The reactor of Claim 128 wherein said separate semiconductor window sections comprise:

- an inner disk top section;
- an outer annulus top section.

5 131. The reactor of Claim 130 wherein said semiconductor window side portion joined with said outer annulus top section.

10 132. The reactor of Claim 130 wherein said semiconductor window side portion is electrically separate from said outer annulus top section and comprises another one of said separate semiconductor window sections.

15 133. The reactor of Claim 114 wherein said overlying top portion of said semiconductor window electrode is generally flat and said inductive antenna is congruent therewith.

134. The reactor of Claim 114 wherein said overlying top portion of said semiconductor window electrode is dome-shaped.

20 135. The reactor of Claim 134 wherein said inductive antenna is congruent with said dome-shaped top portion of said semiconductor window.

25 136. The reactor of Claim 135 wherein said dome-shaped top portion has a multi-radius dome shape having a maximum radius at its periphery and a minimum radius at its interior.

137. The reactor of Claim 100 wherein semiconductor window comprises:

- (a) an overlying top portion; and
- (b) an encircling side portion, said top and side portions of said semiconductor window enclosing a processing region of said chamber for confining plasma over said workpiece.

30 138. The reactor of Claim 137 wherein said encircling side portion extends from said top portion to said workpiece supporting base, said reactor further comprising:

35

a collar between said side portion and said base for blocking plasma flow between said side portion and said base by providing at least one of:

- 5 (a) a narrow passage between said portion and base,
- (b) a meandering passage between said side portion and base.

139. The reactor of Claim 137 further comprising:
a heater thermally coupled to said semiconductor
10 window; and

a cold plate thermally coupled to said semiconductor window.

140. The reactor of Claim 137 further comprising:
a passageway through said semiconductor window
15 electrode, said passageway comprising one of:

- (a) a wafer slit valve aperture,
- (b) a pumping annulus aperture,
- (c) a gas inlet; and

plural plasma confinement magnets adjacent said
20 passageway.

141. The reactor of Claim 140 wherein said passageway comprises a pumping annulus aperture, said reactor further comprising:

a pumping annulus proximal a periphery of said
25 semiconductor window side portion;

a pump coupled to said pumping annulus; and
wherein said passageway extends through said semiconductor window side portion from said processing region to said pumping annulus.

142. The reactor of Claim 140 further comprising a
30 protective encapsulation layer around each of said magnets.

143. The reactor of Claim 141 further comprising a
magnet cooler in thermal contact with at least one of said
35 magnets.

144. The reactor of Claim 140 further comprising a removable liner covering an interior surface of said pumping annulus.

5 145. The reactor of Claim 144 further comprising a liner cooler in thermal contact with said removable liner.

146. The reactor of Claim 137 wherein said gas inlet system comprises plural gas inlets through said semiconductor window.

10 147. The reactor of Claim 146 wherein said plural gas inlets are independently controllable and overlie different radial locations of said workpiece for independently affecting plasma conditions over different radial locations of said workpiece.

15 148. The reactor of Claim 147 wherein said inductive antenna comprises electrically separate sub-antenna portions proximal different respective radial locations of said workpiece.

149. The reactor of Claim 148 wherein said separate sub-antenna portions comprise:

20 an inner antenna winding overlying said top portion of said semiconductor window and overlying a center portion of said workpiece; and

25 an outer annular antenna portion overlying said top portion of said semiconductor window and overlying a peripheral annular portion of said workpiece.

150. The reactor of Claim 149 wherein said separate sub-antenna portions comprise:

a top antenna winding overlying said top portion of said semiconductor window; and

30 a cylindrical side antenna winding wound around said side portion of said semiconductor window.

151. The reactor of Claim 148 wherein said semiconductor window comprises electrically separate sections comprising a center section and a side section and

separate terminals for applying separate RF potentials to said separate sections of said semiconductor window.

152. The reactor of Claim 151 wherein said separate semiconductor window sections are proximal different
5 respective radial locations of said workpiece.

153. The reactor of Claim 151 wherein said separate semiconductor window sections comprise:

an inner disk top section;

an outer annulus top section.

10 154. The reactor of Claim 153 wherein said semiconductor window side portion is joined with said outer annulus top section.

155. The reactor of Claim 153 wherein said semiconductor window side portion is electrically separate
15 from said outer annulus top section and comprises another one of said separate semiconductor window sections.

156. The reactor of Claim 137 wherein said overlying top portion of said semiconductor window is generally flat and said inductive antenna is congruent therewith.

20 157. The reactor of Claim 137 wherein said overlying top portion of said semiconductor window is dome-shaped.

158. The reactor of Claim 157 wherein said inductive antenna is congruent with said dome-shaped top portion of said semiconductor window.

25 159. The reactor of Claim 158 wherein said dome-shaped top portion has a multi-radius dome shape having a maximum radius at its periphery and a minimum radius at its interior.

30 160. An RF plasma reactor chamber for processing a semiconductor wafer and comprising an all non-metallic enclosure for confining plasma within a processing region overlying said wafer.

161. The reactor of Claim 160 wherein said non-metallic enclosure comprises semiconductor material.

162. The reactor of Claim 161 wherein said non-metallic enclosure comprises a dielectric material.

163. The reactor of Claim 161 wherein said semiconductor material comprises one of a class of materials comprising silicon and silicon carbide.

164. The reactor of Claim 162 wherein said dielectric material comprises one of a class of materials comprising silicon nitride, aluminum nitride, quartz and alumina.

165. The reactor of Claim 161 further comprising an electrical terminal connected to said enclosure for applying an electrical potential thereto for promoting continuous cleaning by ion bombardment thereof.

166. The reactor of Claim 161 further comprising a heater and a cooler thermally coupled to said enclosure.

167. The reactor of Claim 166 wherein said enclosure comprises electrically separate overlying top and encircling side portions thereof, and wherein said heater and cooler comprises separately controllable heating and cooling element pairs thermally coupled to respective ones of said top and side portions of said enclosure.

168. The reactor of Claim 160 further comprising:
a passageway through said non-metallic enclosure,
said passageway comprising one of:

- (a) a wafer slit valve aperture,
- (b) a pumping annulus aperture,
- (c) a gas inlet; and

plural plasma confinement magnets adjacent said passageway.

169. The reactor of Claim 168 wherein said passageway comprises a pumping annulus aperture, said reactor further comprising:

a pumping annulus proximal a periphery of said non-metallic enclosure;

a pump coupled to said pumping annulus; and

wherein said passageway extends through said non-metallic enclosure from said processing region to said pumping annulus.

5 170. The reactor of Claim 169 further comprising a protective encapsulation layer around each of said magnets.

171. The reactor of Claim 169 further comprising magnet cooler in thermal contact with at least one of said magnets.

10 172. The reactor of Claim 168 further comprising a removable liner covering an interior surface of said pumping annulus.

173. The reactor of Claim 172 further comprising a liner cooler in thermal contact with said removable liner.

15 174. The reactor of Claim 160 further comprising plural gas inlets through said enclosure.

175. The reactor of Claim 174 wherein said plural gas inlets are independently controllable and proximal different radial locations of said workpiece for independently affecting plasma conditions over different radial locations of said workpiece.

20 176. The reactor of Claim 175 wherein said inductive antenna comprises electrically separate sub-antenna portions proximal different respective radial locations of said workpiece.

25 177. The reactor of Claim 176 wherein said separate sub-antenna portions comprise:

30 an inner antenna winding overlying said top portion of said enclosure and overlying a center portion of said workpiece; and

an outer annular antenna portion overlying said top portion of said enclosure and overlying a peripheral annular portion of said workpiece.

35 178. The reactor of Claim 177 wherein said separate sub-antenna portions comprise:

a top antenna winding overlying said top portion of said enclosure; and

a cylindrical side antenna winding wound around said side portion of said enclosure.

5 179. The reactor of Claim 176 wherein said enclosure comprises electrically separate sections comprising a center section and a side section and separate terminals for applying separate RF potentials to said separate sections of said enclosure.

10 180. The reactor of Claim 179 wherein said separate enclosure sections are proximal different respective radial locations of said workpiece.

181. The reactor of Claim 179 wherein said separate enclosure sections comprise:

15 an inner disk top section;
 an outer annulus top section.

182. The reactor of Claim 181 wherein said enclosure side portion joined with said outer annulus top section.

20 183. The reactor of Claim 181 wherein said enclosure side portion is electrically separate from said outer annulus top section and comprises another one of said separate enclosure sections.

25 184. The reactor of Claim 167 wherein said overlying top portion of said enclosure is generally flat and said inductive antenna is congruent therewith.

185. The reactor of Claim 167 wherein said overlying top portion of said enclosure is dome-shaped.

30 186. The reactor of Claim 185 wherein said inductive antenna is congruent with said dome-shaped top portion of said enclosure.

187. The reactor of Claim 186 wherein said dome-shaped top portion has a multi-radius dome shape having a maximum radius at its periphery and a minimum radius at its interior.

188. The reactor of Claim 160 further comprising a wafer pedestal for supporting a semiconductor wafer for processing within said reactor, and wherein said enclosure comprises a center enclosure piece and a side enclosure piece electrically insulated from said center enclosure piece, said reactor further comprising:

first and second RF power sources coupled respectively to two of said center enclosure piece, side enclosure piece and said pedestal, said first and second RF power sources providing RF power at first and second RF frequencies respectively; and

RF filters for isolating each one of said first and second RF power sources from the RF frequency of the other.

189. The reactor of Claim 160 further comprising:
at least a passage through said enclosure.

190. The reactor of Claim 189 further comprising:
a plasma confinement magnet proximal said passage.

191. The reactor of Claim 189 wherein said passage has a narrow aspect ratio for promoting recombination of plasma within said passage.

192. The reactor of Claim 189 wherein said passage provides a meandering path for promoting recombination of plasma within said passage.

193. A method of processing a semiconductor wafer in an RF plasma reactor having a base for supporting the wafer within a chamber of the reactor, said method comprising:

providing an enclosure for confining a plasma within a processing region of the chamber over said wafer;
preventing deposition of plasma-processing by-products on said enclosure.

194. The method of Claim 193 wherein the step of preventing deposition comprises at least one of:

(a) maintaining a temperature of said enclosure above a threshold condensation temperature; and

(b) applying an RF potential to said enclosure to promote sputtering of said enclosure during plasma processing of said wafer.

5 195. The method of Claim 194 wherein the step of preventing deposition comprises both (a) and (b).

196. The method of Claim 193 wherein said reactor comprises a passageway through said enclosure, said passageway comprising one of (a) a wafer slit valve aperture, (b) a pumping annulus aperture, (c) a gas inlet, said method further comprising:

10

preventing escape of charge particles from said processing region through said passageway.

197. The method of Claim 196 wherein the step of preventing escape of charge particles through said passageway comprises constricting said passageway to at least one of:

15

(a) a narrow channel, and

(b) a meandering channel.

198. The method of Claim 196 wherein the step of preventing escape of charge particles through said passageway comprises:

20

placing plasma confinement magnets proximal said passageway.

199. The method of Claim 198 wherein said plasma confinement magnets comprise a pair of magnets facing each other across said aperture and having their magnetic poles aligned so as to impart a lateral acceleration to charged particles traveling through said passageway.

25

200. The method of Claim 198 further comprising providing protective encapsulation around each of said plasma confinement magnets.

30

201. The method of Claim 198 further comprising cooling said plasma confinement magnets.

202. The method of Claim 193 wherein said reactor has an evacuation pump and a pumping annulus surrounding a

35

periphery of said enclosure and an aperture through said enclosure for permitting gas flow from said processing region to said pumping annulus, said method further comprising:

5 providing a liner over an interior surface of said pumping annulus; and

 causing condensation on said liner of plasma-processing by-products that have entered said pumping annulus.

10 203. The method of Claim 202 wherein the step of causing condensation comprises maintaining a temperature of said liner below a threshold condensation temperature.

 204. The method of Claim 193 wherein said enclosure is formed of semiconductor material and wherein said method
15 further comprises:

 coupling plasma RF source power through said enclosure into said processing region.

 205. The method of Claim 198 wherein said reactor further includes an inductive coil proximal an exterior
20 surface of said enclosure, and wherein the step of coupling plasma RF source power comprises inductively coupling plasma RF source power from said inductive coil through said enclosure.

 206. The method of Claim 205 wherein the step of
25 inductively coupling comprises inductively coupling different amounts of RF power through different radial locations of said enclosure relative to said wafer.

 207. The method of Claim 206 further comprising
30 applying different RF potentials to different radial zones of said enclosure.

1/55




FIG. 1




FIG. 2




FIG. 3




FIG. 4

3/55




FIG. 5




FIG. 6




FIG. 7




FIG. 8




FIG. 9




FIG. 10




FIG. 11




FIG. 12




FIG. 14




FIG. 15

8/55




FIG. 13A




FIG. 13B




FIG. 13C




FIG. 13D

10/55




FIG. 16




FIG. 18




FIG. 17A




FIG. 17B

12/55




FIG. 19






FIG. 20






FIG. 23

15/55




FIG. 24

16/55




FIG. 25A




FIG. 25B




FIG. 25C




FIG. 26




FIG. 27




FIG. 28




FIG. 29




FIG. 30A




FIG. 30B




FIG. 30C

19/55




FIG. 31A




FIG. 31B




FIG. 31C

20/55




FIG. 32




FIG. 33




FIG. 34

21/55




FIG. 35A




FIG. 35B




FIG. 35D




FIG. 35C




FIG. 35E

22/55




FIG. 36A




FIG. 36B




FIG. 37A




FIG. 37B




FIG. 38A




FIG. 38B




FIG. 39A




FIG. 39B




FIG. 40




FIG. 41A




FIG. 41B




FIG. 42




FIG. 43




FIG. 44




FIG. 45

31/55




FIG. 46






FIG. 47








FIG. 48C




FIG. 49




FIG. 50




FIG. 51





FIG. 52






FIG. 54






FIG. 55








FIG. 58




FIG. 59

46/55




FIG. 60

47/755




FIG. 61





FIG. 62






FIG. 64




FIG. 65




FIG. 66




FIG. 67




FIG. 68A

FIG. 68B




FIG. 68C

FIG. 68D

FIG. 68E




FIG. 69

INTERNATIONAL SEARCH REPORT

International Application No
PC./US 96/14157

A. CLASSIFICATION OF SUBJECT MATTER IPC 6 H01J37/32		
According to International Patent Classification (IPC) or to both national classification and IPC		
B. FIELDS SEARCHED Minimum documentation searched (classification system followed by classification symbols) IPC 6 H01J		
Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched		
Electronic data base consulted during the international search (name of data base and, where practical, search terms used)		
C. DOCUMENTS CONSIDERED TO BE RELEVANT		
Category *	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
A	EP,A,0 520 519 (APPLIED MATERIALS INC) 30 December 1992 cited in the application see page 7, line 32 - line 33; figures 1-3 ---	1,101, 160,193
A	EP,A,0 552 491 (APPLIED MATERIALS INC) 28 July 1993 see page 7, line 25 - line 47; figures 1-3 ---	1,101, 160,193
P,A	EP,A,0 680 072 (APPLIED MATERIALS INC) 2 November 1995 see column 7, line 9 - line 37; figure 1 --- -/--	1,101, 160,193
<div style="display: flex; justify-content: space-between;"> <input checked="" type="checkbox"/> Further documents are listed in the continuation of box C. <input checked="" type="checkbox"/> Patent family members are listed in annex. </div>		
<div style="display: flex;"> <div style="flex: 1;"> <p>* Special categories of cited documents :</p> <p>*A* document defining the general state of the art which is not considered to be of particular relevance</p> <p>*E* earlier document but published on or after the international filing date</p> <p>*L* document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)</p> <p>*O* document referring to an oral disclosure, use, exhibition or other means</p> <p>*P* document published prior to the international filing date but later than the priority date claimed</p> </div> <div style="flex: 1;"> <p>*T* later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention</p> <p>*X* document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone</p> <p>*Y* document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art.</p> <p>*&* document member of the same patent family</p> </div> </div>		
Date of the actual completion of the international search <div style="text-align: center; font-weight: bold;">17 December 1996</div>		Date of mailing of the international search report <div style="text-align: center; font-weight: bold;">3.01.97</div>
Name and mailing address of the ISA European Patent Office, P.B. 5818 Patentlaan 2 NL - 2280 HV Rijswijk Tel. (+ 31-70) 340-2040, Tx. 31 651 epo nl, Fac (+ 31-70) 340-3016		Authorized officer <div style="text-align: center; font-weight: bold;">Schaub, G</div>

INTERNATIONAL SEARCH REPORT

International Application No

PC./US 96/14157

C.(Continuation) DOCUMENTS CONSIDERED TO BE RELEVANT

Category *	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
A P,A	DATABASE WPI Section Ch, Week 9529 Derwent Publications Ltd., London, GB; Class L03, AN 95-218685 XP002021474 & JP,A,07 130 497 (NEC CORP) , 19 May 1995 see abstract & US,A,5 470 426 (YOSHIDA) 28 November 1995 -----	1,101, 160,193

INTERNATIONAL SEARCH REPORT

Information on patent family members

International Application No

PC/US 96/14157

Patent document cited in search report	Publication date	Patent family member(s)	Publication date
EP-A-0520519	30-12-92	JP-A- 5206072	13-08-93
		US-A- 5556501	17-09-96
		US-A- 5574410	12-11-96
		US-A- 5572170	05-11-96
		US-A- 5392018	21-02-95
		EP-A- 0552490	28-07-93
		EP-A- 0552491	28-07-93

EP-A-0552491	28-07-93	EP-A- 0520519	30-12-92
		EP-A- 0552490	28-07-93
		JP-A- 5206072	13-08-93
		JP-A- 6112166	22-04-94

EP-A-0680072	02-11-95	JP-A- 8092748	09-04-96
